

**PERFORMANCE EVALUATION OF
WIRELESS MULTICARRIER MODEM WITH
DQPSK MODULATION FOR HF COMMUNICATIONS**

ABDULL ZUBI BIN AHMAD

**A project report submitted in partial fulfillment of the
requirements for the award of the degree of
Master of Engineering (Electrical - Electronics & Telecommunications)**

**Faculty of Electrical Engineering
Universiti Teknologi Malaysia**

MARCH 2005

ACKNOWLEDGEMENTS

First and foremost praise be to Allah for giving me the good health to complete this project thesis.

I would like to sincerely thank my supervisor Professor Madya Dr. Ahmad Zuri Bin Sha'ameri for all the help and guidance in the work towards the writing up of this thesis. Dr. Zuri has always been an excellent provider of new ideas and enriched our regular meetings with very useful comments.

A very special thank should also go to my wife and children for giving me all the necessary support and encouragements during the course of this MEng programme till this thesis writeup.

Last but not least, I would also like to express my gratitude to GMI and UTM for all services rendered to me during the course of this Masters programme at the university.

ABSTRAK

Tesis ini membentangkan pencapaian kadar kesilapan bit dan analisis efisiensi bagi modem pelbagai pembawa isyarat tanpa wayar menerusi gelombang radio berfrekuensi tinggi untuk perkhidmatan audio dan data berdasarkan modulasi DQPSK di dalam keadaan kebisingan AWGN dan saluran pancaran Rayleigh. Ia menggabungkan dua teknologi – HF atau frekuensi tinggi di antara 3 – 30 MHz bagi menyediakan sambungan komunikasi jarak jauh tanpa wayar (seperti yang digunakan di dalam ketenteraan) berserta teknologi pelbagai pembawa isyarat modem yang memisahkan satu jalur saluran kepada banyak saluran kecil berbanding dengan pancaran isyarat yang menggunakan satu pembawa, untuk membolehkan tempoh simbol yang lebih panjang. Tempoh simbol yang lebih panjang ini dapat mengelakkan gangguan intersimbol yang disebabkan oleh kepincangan saluran pelbagai arah akibat taburan lambat masa isyarat hasil dari kesan semulajadi lapisan ionosfera yang dilalui oleh isyarat HF yang digunakan.

Selain daripada kegunaannya di dalam bidang ketenteraan, teknologi ini boleh juga diaplikasikan untuk sambungan komunikasi luar bandar. Infrastruktur komunikasi luar bandar diselubungi dengan pelbagai masalah seperti jarak komunikasi yang sangat jauh dan ditambah pula dengan taburan penduduk yang tidak seimbang. Justeru itu, pembangunan infrastruktur yang sangat mahal seperti penggunaan sambungan satelit atau sambungan talian jarak jauh perlu digunakan yang tidak dapat mendatangkan keuntungan malah merugikan. Oleh itu satu sistem komunikasi yang menggunakan modem menerusi teknik modulasi pelbagai pembawa isyarat berserta pancaran gelombang HF melalui ionosfera dibentangkan di dalam tesis ini bagi memberikan suatu penyelesaian untuk masalah yang tersebut atas.

ABSTRACT

This thesis presents the bit error rate performances and throughput analysis over an HF radio channel using wireless multicarrier modem for voice and data services based on differential quaternary phase shift keying or DQPSK modulation in the presence of additive white Gaussian noise (AWGN) affected by slow Rayleigh fading. It combines two technologies – the high-frequency or HF band in the range of 3 – 30MHz to provide wireless long-distance and repeaterless communication links (eg. as used in the military) as well as multicarrier or parallel modem technology that provides simultaneous operations with the suppression of multipath components and other phenomena introduced by the ionosphere and also other narrowband interferences.

In addition to conventional military applications for the fading radio channel, this implementation is also suitable for point-to-point links in the HF rural telecommunications area. The communications infrastructure for rural populations poses several problems which includes the generally long distances involved over which communication takes place as well as the low population densities which are also sparsely distributed. Thus, very expensive infrastructures like satellite links or long-haul repeater systems need to be employed which is aggravated by the fact that rural communities are in no position to pay for such facilities. A solution would thus require low cost wireless equipments incorporating HF and multicarrier technologies connecting the widely separated communities together as well as to the outside world. It is to be noted that multicarrier communication which employs HF radio technology will do away with third party equipments as well as the per-minute costs associated with satellite services.

TABLE OF CONTENTS

CHAPTER	TITLE	PAGE
	THESIS STATUS VALIDATION	i
	SUPERVISOR'S DECLARATION	ii
	TITLE PAGE	iii
	ACKNOWLEDGEMENT	iv
	ABSTRAK	v
	ABSTRACT	vi
	TABLE OF CONTENTS	vii
	LIST OF FIGURES	x
	LIST OF TABLES	xii
	LIST OF SYMBOLS	xiii
	LIST OF APPENDICES	xv
1	INTRODUCTION	
	1.1 Overview	1
	1.2 Objective	2
	1.3 Scope	3
	1.4 Problem Statement	3
	1.5 Research Methodology	4

2	LITERATURE REVIEW	
2.1	Current Implementations of Multicarrier Systems	6
2.2	Implementation Issues of Multicarrier Systems	8
3	THEORY OF OPERATION OF MULTICARRIER SYSTEMS	
3.1	Multicarrier Basics	9
3.2	Path Loss Model for Ionospheric HF Channel	12
3.3	Multipath Effects	14
3.4	Time Delay Spread	15
3.5	Timing Offset Estimation	17
3.6	DFT Implementations of Multicarrier Tx and Rx	18
3.7	Other Impairments	19
3.8	Methods to Achieve a Low PAPR	21
3.9	How Multicarrier HF is Different from Singlecarrier Systems	22
4	DPSK AND DQPSK IN MULTICARRIER HF SYSTEMS	
4.1	Introduction to Singlecarrier DPSK	26
4.2	Retrieving Data at a Singlecarrier DPSK Receiver	27
4.3	Introduction to Multicarrier DPSK	29
4.4	DQPSK in Multicarrier Systems	32
5	HF RADIO PROPAGATION AND RAYLEIGH FADING EFFECTS	
5.1	The Ionosphere and its Structure	34
5.2	Production and Loss of Electrons in the Ionosphere	36
5.3	Methods of Observing the Ionosphere	37
5.4	Ionospheric Variations Affecting HF Communications	39
5.5	Types of HF Propagation and Usable Frequency Range	40
5.6	HF Communication Hop Lengths	41
5.7	Frequency, Range and Elevation Angles	42
5.8	Skip Zones in HF Communications	45

5.9	Noise Effects in HF Communications	45
5.10	Fading in HF Communications Channel	46
5.11	Types of Fading Effects	49
5.12	Small-scale Fading (Rayleigh Fading)	50
5.13	Frequency-selective and Flat Fading	50
5.14	Using Multicarrier and Differential Modulation to Mitigate Rayleigh Fading	52
5.15	Effects of Doppler Frequency Shifts on Multicarrier DQPSK	54
5.16	Tactical Military HF Radio Communications Using IP	58

6 SYSTEM HF MODEL USED FOR SIMULATIONS

6.1	Multicarrier HF Model used for Simulations	60
6.2	System Specifications used for Project	63

7 RESULTS AND DISCUSSIONS

7.1	BER vs SNR Performance for Singlecarrier QPSK	64
7.2	BER vs SNR Performance for Singlecarrier DQPSK	66
7.3	BER vs SNR Performance of Multicarrier DPSK and DQPSK	67
7.4	Throughput Analysis of the Multicarrier DQPSK HF Modem	72
7.5	Multicarrier HF Modem System Throughput in AWGN	75
7.6	HF Modem System Throughput in Rayleigh Fading	82
7.7	Factors to Increase Throughput for Tactical HF Communications	84
7.8	Conclusions	85
7.9	Suggestions for Further Work	86

REFERENCES	89
-------------------	----

APPENDIX – Matlab Programs used for Simulations	92
--	----

LIST OF FIGURES

FIGURE NO.	TITLE	PAGE
Figure 3.1.1	Typical Multicarrier HF Modem Transmitter	9
Figure 3.1.2	Typical Multicarrier HF Modem Receiver	9
Figure 3.1.3	Multicarrier Modem using Differential Encocding	10
Figure 3.1.4	Modulation by Baseband Processing	11
Figure 3.2.1	Path Loss and Propagation Modes in Fading Ionospheric HF Channel	13
Figure 3.3.1	Effects of Constructive & Destructive Interference	13
Figure 3.3.2	Variation of Received Signal Power in a Fading Channel	14
Figure 3.4.1	Two-Ray Model	15
Figure 3.4.2	Time-Delay Spread and ISI	15
Figure 3.4.3	Flat Fading and Frequency-Selective Fading	16
Figure 3.4.4	Bitrate Limitations Imposed by ISI	16
Figure 3.5.1	Cyclic Prefix in Multicarrier Systems	18
Figure 3.7.1	Peak-to-Average Power Ratio in Multicarrier Systems	20
Figure 3.8.1	Selective Mapping to Achieve Low PAPR	21
Figure 4.1.1	Block Diagram of Singlecarrier DPSK Transmitter	26
Figure 4.2.2	Block Diagram of Singlecarrier DPSK Receiver	28
Figure 4.2.3	Error Performance Comparison Betw. Singlecarrier DPSK and BPSK	29
Figure 4.3.1	Block Diagram of a Multicarrier DPSK Modulation System	31
Figure 4.4.1	IQ Diagrams for DPSK and DQPSK	32
Figure 5.1.1	Day and Night Structure of the Ionosphere	36
Figure 5.2.1	Production of Electrons in the Ionosphere	37
Figure 5.2.2	Loss of Electrons in the Ionosphere	37
Figure 5.3.1	Ionosonde Operation	38
Figure 5.5.1	Types of HF Propagation	41
Figure 5.6.1	Hop Lengths Based on Antenna Elevation Angles	42
Figure 5.7.1	Elevation Angle Fixed Case	43
Figure 5.7.2	Path Length Fixed Case	44
Figure 5.7.3	Frequency Fixed Case	44
Figure 5.10.1	Multipath Fading in HF Channel	46

Figure 5.10.2	Focussing and Defocussing Effects Caused by HF Tilting and TIDs	47
Figure 5.15.1	Frequency Spectrum of Interference Due to Doppler Effect	55
Figure 5.15.2	Directions of Differential Detection for DQPSK	56
Figure 5.15.3	Phase Shift Caused by Doppler Frequency Shift	56
Figure 5.16.1	A model of IP networks connected by HF for NATO	59
Figure 6.1.1	Typical Multicarrier HF Radio Communication System	60
Figure 6.1.2	Multicarrier HF Model Used for Simulations	62
Figure 7.1.1	Error Rate Performance of Singlecarrier QPSK	64
Figure 7.1.2	Error Rate Performance of Singlecarrier BPSK	65
Figure 7.2.1	Error Rate Performance of Singlecarrier DQPSK	66
Figure 7.3.1	Error Rate Performance of Multicarrier DPSK for $t_s=1$	68
Figure 7.3.2	Error Rate Performance of Multicarrier DQPSK for $t_s=1$	68
Figure 7.3.3	Error Performance of Multicarrier DPSK and DQPSK for $t_s=1$	69
Figure 7.3.4	Error Rate Performance of Multicarrier DQPSK for $t_s=4$	70
Figure 7.3.5	Error Rate Performance of Multicarrier DQPSK for $t_s=16$	71
Figure 7.3.6	Error Rate Performance of Multicarrier DQPSK for $t_s=1, 4, 16$	71
Figure 7.4.1	Error Probability vs SNR/bit for BPSK	72
Figure 7.4.2	Channel Capacity vs SNR/bit for BPSK	73
Figure 7.5.1	Throughput vs SNR for Const. Trans. Rate C and Block Length = 64 bits	77
Figure 7.5.2	Throughput vs SNR for Const. Trans. Rate C and Block Length = 128 bits	77
Figure 7.5.3	Throughput vs SNR for Constant C and B = 64 bits and 128 bits	78
Figure 7.5.4	Throughput vs SNR for Const. B = 154 bits and Trans. Rate = $C/4$	80
Figure 7.5.5	Throughput vs SNR for Const. B = 154 bits and Trans. Rate = C	81
Figure 7.5.6	Throughput vs SNR for Const. B = 154 bits and Trans. Rate = C and $C/4$	82

LIST OF TABLES

TABLE NO.	TITLE	PAGE
Table 3.4.1	Time Delay Spread and Maximum Bitrate	17
Table 4.1.1	DPSK Encoding at Transmitter	27
Table 4.2.1	DPSK Detection at Receiver	27
Table 4.4.1	Phase Mapping for DQPSK	33
Table 6.2.1	Proposed System Specifications	63
Table 7.3.1	Results of BER vs SNR of Multicarrier DPSK and DQPSK	67
Table 7.5.1	Results of Multicarrier HF Throughput for Const.C and Variable B	76
Table 7.5.2	Results of Multicarrier HF Throughput for Const.B and Variable C	80

LIST OF SYMBOLS

ADSL	Asynchronous Digital Subscriber Line
ARQ	Automatic Repeat Request
ASK	Amplitude Shift Keying
AWGN	Additive White Gaussian Noise
BER	Bit Error Rate
BPSK	Binary Phase Shift Keying
CDMA	Code Division Multiple Access
CRC-16	Cyclic Redundancy Check – 16
CRC-32	Cyclic Redundancy Check – 32
DAB	Digital Audio Broadcasting
DFT	Discrete Fourier Transform
DPSK	Differential Phase Shift Keying
DQPSK	Differential Quaternary Phase Shift Keying
DSP	Digital Signal Processing
DTV	Digital Television
DVB-T	Digital Video Broadcasting – Terrestrial
FDM	Frequency Division Multiplexing
FEC	Forward Error Correction
FFT	Fast Fourier Transform
FSK	Frequency Shift Keying
HF	High Frequency (3 – 30 MHz)
ICI	Intercarriers Interference
IDFT	Inverse Discrete Fourier Transform
IFFT	Inverse Fast Fourier Transform

ISI	Intersymbol Interference
LAN	Local Area Network
LOS	Line of Sight
MCM	Multicarrier Modulation
NATO	North Atlantic Treaty Organisation
OFDM	Orthogonal Frequency Division Multiplexing
PSK	Phase Shift Keying
QAM	Quadrature Amplitude Modulation
QOS	Quality of Service
QPSK	Quaternary Phase Shift Keying
SNR	Signal to Noise Ratio
TDM	Time Division Multiplexing
WLL	Wireless Local Loop

LIST OF APPENDICES

APPENDIX	TITLE	PAGE
A	Matlab Codes Used for Project Simulations	92

CHAPTER 1

INTRODUCTION

1.1 Overview

Historically, parallel or multicarrier radio modems have been the first high frequency modem to provide high datarate wireless communications. In particular in the 1960's, this technique was used in several HF military systems viz., Kineplex [Doelz, 1957] and Kathryn [Bello, 1965]. High datarate serial radio modem appeared as soon as it was possible to implement adaptive algorithms that are required for equalization. Nevertheless, the equalization algorithm became more and more complex when higher datarate needed to be transmitted over the HF band and hence a parallel or multicarrier solution was called for.

A multicarrier modem system is a technique that transmit data by dividing it into several interleaved bit streams and using these to modulate several subcarriers in turn. It has been shown to be an effective technique to combat multipath fading in wireless communication systems. It has been successfully used for military HF radio applications and is also the standard for digital audio broadcasting and digital terrestrial TV broadcasting in Europe and high-speed wireless local area networks.

This thesis will evaluate the performance and perform a throughput analysis of a multicarrier radio modem employing Differential Quaternary Phase Shift Keying or DQPSK in a Rayleigh fading radio channel affected by additive white Gaussian noise or AWGN. The majority of multicarrier modems in the market uses coherent modulation as the digital modulation methods. This project thesis concerns about the use of DQPSK since it is not very sensitive to phase error (as in the case of a coherent system) and also comparatively simpler and cheaper to implement.

1.2 Objectives

This research work investigates the performances of a multicarrier radio modem system using DQPSK with 2-bit encoding as the digital modulation method in the presence of AWGN environment only as well as AWGN with Rayleigh fading channel. It will also compare the performances with binary DPSK modulation which uses single bits to encode sequences of binary data. A throughput analysis of the system will also be presented for the multicarrier DQPSK case.

In the past several years, there have been many studies being carried out concerning multicarrier systems for use in a wide variety of wireless communications applications mainly using coherent PSK and QAM as the digital modulation methods. The great interest is due to their bandwidth-efficient property and good error performances in a challenging radio environment. But these are complex coherent systems that require the use of expensive receivers with equalization for carrier phase recovery in order to prevent phase ambiguities in the detection process at the receiver.

For the purpose of this research work, the candidate will attempt to investigate the use of DQPSK modulation with 2-bit differential encoding. In this technique, the information is encoded in the phase transitions rather than in the actual phase value. The process of differential encoding, phase shift keying, detection and differential decoding is immune to any phase ambiguity and allows suboptimum differential detection to be carried out. In this case, a carrier phase recovery circuit is not needed since the relative phases of the consecutive received symbols is what is important. And this suboptimum detection strategy is an attractive proposition in wireless applications where phase changes are difficult to track without expensive hardware.

The multicarrier HF radio modem system for this project also uses the (inverse) Fast Fourier Transform technique to orthogonally multiplex many narrow subchannels, each signalling at a relatively low rate, into one high datarate channel. With each subchannel signalling at a low rate, the multicarrier technique can provide added protection against delay spread. To enhance the behaviour of the system in a heavily frequency-selective HF environment, bit-interleaving of the symbol data will also be performed in order to randomize the data for better detection process at the DQPSK receiver. This is achieved by differentially encoding the input data stream between frames across the time axis making up the multicarrier signal.

1.3 Scope

There are generally two classes of HF radio modems in use today, viz. the singletone or serial (ie. singlecarrier) system and the multitone or parallel (ie. multicarrier) system. This project thesis is a comparison study on the bit error rate performances between multicarrier DPSK systems with a multicarrier DQPSK system in an HF channel corrupted with AWGN noise only as well as one which is corrupted with AWGN noise and at the same time affected by slow (Rayleigh) fading. A throughput analysis of the multicarrier DQPSK system will also be carried out in order to determine the parameters involved which affects the performance of the radio modem. As a start, error rate performance comparisons will be made between singlecarrier QPSK and singlecarrier DQPSK in order to show that coherent systems have better error rate performances compared to differential systems. Subsequent to that, comparisons between DPSK and DQPSK multicarrier systems will be made. The Rayleigh fading radio channel has been chosen as it closely resembles the actual channel characteristics of current HF radio channels in which the great majority of signal transmission and reception are non line-of-sight with multipath condition. Measurements confirm that the short-term statistics of the resultant signal envelope approximate a Rayleigh distribution.

1.4 Problem Statement

Current multicarrier modulation systems employing coherent PSK and QAM have several disadvantages – they have good error performance quality but require complex and expensive filter banks as well as channel equalizers at the receiver. However the luxury of an expensively-designed multicarrier systems mentioned above could be economically-justified by telecommunications and broadcasting operators worldwide due to the high returns involved.

But if cost is a factor as in the provision of rural telecommunication services or in military applications where long-distance repeaterless communication is a necessity without third party involvement (like the use of an intermediate satellite link that can be open to sabotage and enemy transgression), then alternative but cheaper designs which can be more secure will have to be considered (The ionosphere, over which HF communications takes place, unlike satellites, cannot

be destroyed). One possible approach is to use some form of differential modulation and demodulation technique for transmission and detection. Singlecarrier DQPSK by itself does not produce very good error performances compared to coherent PSK and QAM systems. But it could be implemented in systems requiring simpler designs with cost-effective receivers. Therefore if it is to be implemented in conjunction with a multicarrier system with the inherent advantages that it can offer like reduction of multipath effects and intersymbol interferences, it will definitely help improve the error performance statistics apart from being comparatively simpler and cheaper to design since now the requirements of channel filtering and carrier recovery circuits as well as equalization can be done away with.

1.5 Research Methodology

Literature reviews on the topics related to HF multicarrier implementations are necessary in order to have a clear understanding on the research areas currently undertaken or that which have already been carried out by researchers worldwide. It is also crucial to understand the assumptions made and the aspects which have been taken into considerations that contribute to the development of HF multicarrier systems. For this purpose, on-line publications from IEE and IEEE are of great help.

From the reviews that have been done by the candidate up to this point in time, it was discovered that the vast majority of HF multicarrier systems are being implemented using coherent modulation methods which are either PSK-based or QAM. These methods require the use of expensive filtering and equalization techniques in order to transmit signals in a bandlimited and challenging channel environment apart from having to mitigate the effects of a non-uniform (ie. variable) and fading channel. However, there must be good reasons to support these trends which might be due to the very good error performances attained by those modulations.

But it must also be pointed out that this is true for commercial communication systems like wireline assymetric digital subscriber line or ADSL for fast internet access, digital line-of-sight microwave transmissions, terrestrial digital radio and television broadcasting systems, data transmission over mobile cellular channels as well as in wireless LANs where there exist large subscriber bases in addition to their usage being already well established. This is unlike the case

for long-distance and repeaterless wireless military applications as well as for rural telecommunications.

In order to generate the data signal, encode it, modulate, transmit and thereafter affected by AWGN with multipath fading on the channel, an analysis on the error performances of the multicarrier system at the receiver after demodulation and detection process could be done with programs written and simulations carried out. For this purpose, Matlab 6 will be used as the computer programming and analysis tool that will help in the simulation work. This requires then that the candidate be proficient in programming using Matlab. Books and references that deal with programming communication systems using Matlab will have to be consulted. Subjects that have been taken by the candidate during the course of this masters programme have become invaluable. These include Advanced DSP and Advanced Digital Communication Systems which have been previously taught by this candidate's supervisor.

At the end of this research work, comparisons on the error performances between multicarrier DPSK with multicarrier DQPSK system in a Rayleigh fading radio channel will be carried out and results compiled, tabled and graphed.

Throughput analysis concerning the performance of multicarrier DQPSK radio modems will also be performed in order to determine the parameters that may further affect its performance.

It is predicted that it will lead to the following conclusions:

- (a) The error rate performance of QPSK will be better than DQPSK for the case of singlecarrier HF modems.
- (b) The error rate performance of multicarrier DPSK will be better than multicarrier DQPSK with the exception that multicarrier DQPSK is more spectrally-efficient than the former. Therefore if higher SNR is available, then DQPSK is more attractive due to its higher capacity.
- (c) Lowering the transmission rate through the HF radio channel will improve the bit error rate and throughput performance for a given SNR for a multicarrier DQPSK modem.
- (d) Increasing the block or packet length through the HF radio channel with data transmission rate constant will improve the throughput performance of the DQPSK multicarrier modem.

REFERENCES

- [**R.E. Ziemer and W.H. Tranter**], *Principles of Communications, 4th Edition* (1995)
- [**R.F. Pawula**], *A New Formula for MDPSK Symbol Error Probability, IEEE Comm. Letters, Vol. 2, Oct 1998*
- [**J.H. Park**], *On Binary DPSK Reception, IEEE Trans. Comm., April 1978*
- [**V.K. Prabhu**], *Error Rate Performance for Diff. PSK, IEEE Trans. Comm. Dec 1982*
- [**R. Pawula**], *Asymptotics and Error Rate Bounds for M-ary DPSK, IEEE Trans. Comm. Jan 1984*
- [**J.G. Proakis**], *Digital Communications, 3rd Edition* (New York 1995)
- [**IEEE JSAC**], *Special Issues on Bandwidth and Power Efficient Coded Modulation, Aug and Dec 1989*
- [**IEEE Comm. Magazine**], *Special Issues on Bandwidth and Power Efficient Modulation, Dec 1991*
- [**P.A. Bello**], *Selective Fading Limitations of the Kathryn Modem and Some System Design Considerations, IEEE Trans. Comm. Sept 1965*
- [**J.A.C. Bingham**], *Multicarrier Modulation for Data Transmission : An Idea Whose Time Has Come, IEEE Comm. Magazine, May 1990*
- [**H. Sari, G. Karam**], *Transmission Techniques for Digital Terrestrial TV Broadcasting, IEEE Comm. Magazine, Feb 1995*
- [**R.W. Chang, R.A. Gibby**], *A Theoretical Study of Performance of an Orthogonal Multiplexing Data Transmission Scheme, IEEE Trans. Comm. Aug 1968*
- [**B. Hirosaki**], *An Orthogonally Multiplexed QAM System Using the Discrete Fourier Transform, IEEE Trans. Comm. July 1981*
- [**S.B. Weinstein, P.M. Ebert**], *Data Transmission by FDM Using the DFT, IEEE Trans. Comm. Oct 1971*
- [**L. Cimini**], *Analysis and Simulation of a Digital Mobile Channel Using OFDM, IEEE Trans. Comm. July 1985*
- [**T. Walzman, M. Schwartz**], *Automatic Equalization Using the Discrete Frequency Domain, IEEE Trans. Infor. Theory, Jan 1973*
- [**H. Sari, G. Karam**], *An Analysis of OFDM for Mobile Radio Applications, IEEE VTC Proc. June 1994*
- [**J. A. Davis and J. Jedwab**], *Peak-to-Mean Power Control in OFDM, Golay Complementary Sequences and Reed-Muller Codes Dec. 97.*

- [**S.K. Wilson**], *Digital Audio Broadcasting in a Fading and Dispersive Channel*, PhD Dissertation, Stanford University Aug 1994
- [**H. Sari, G. Karam**], *Frequency Domain Equalization of Mobile Radio Terrestrial Broadcast Channels*, *IEEE Globecom Proc. Dec 1994*
- [**J.J. Van de Beek**], *On Channel Estimation in OFDM Systems*, *IEEE VTC Proc. 1995*
- [**M. Russel, G. Stuber**], *Interchannel Interference Analysis of OFDM in a Mobile Environment*, *IEEE VTC Proc. July 1995*
- [**P. Bello, B. Nelin**], *The Effects of Frequency Selective Fading on the Binary Error Probabilities of Coherent and Differentially Coherent Matched Filter receivers*, *IEEE Trans. Comm. Sys. June 1963*
- [**R. O'Neill, L. Lopes**], *Performance of Amplitude Limited Multitone Signals*, *IEEE VTC Proc. June 1995*
- [**T. Wilkonson, A. Jones**], *Minimisation of the Peak-to-Mean Envelope Power Ratio of Multicarrier Transmission Schemes by Block Coding*, *IEEE VTC Proc. July 1995*
- [**G. Santella, F. Mazzenga**], *A Model for Performance Evaluation in M-QAM OFDM Schemes in the Presence of Nonlinear Distortions*, *IEEE VTC Proc. July 1995*
- [**F. Daffara, A. Chouly**], *Maximum Likelihood Frequency Detectors for Orthogonal Multicarrier Systems*, *IEEE ICC Proc. May 1993*
- [**F. Daffara, O. Adami**], *A New Frequency Detector for Orthogonal Multicarrier Trans. Techniques*, *IEEE VTC Proc. July 1995*
- [**F. Classen, H. Meyr**], *Frequency Synchronization Algorithms for OFDM Systems Suitable for Comm. Over Freq. Selective Fading Channels*, *IEEE VTC Proc. June94*
- [**M.L. Doelz**], *Binary Data Trans. Technique for Linear Systems*, *Proc. IRE May 1957*
- [**R.W. Chang**], *Synthesis of Bandlimited Orthogonal Signals for Multichannel Data Transmission*, *Bell System Tech. Journal, Dec 1966*
- [**R. Saltzberg**], *Performance of an Efficient Parallel Data Transmission System*, *IEEE Trans. Comm. Tech. Dec 1967*
- [**B. Hirosaki**], *An Analysis of Automatic Equalizers for Orthogonally Multiplexed QAM Systems*, *IEEE Trans. Comm. Jan 1980*
- [**W. Henkel, A. Johannson**], *The Cyclic Prefix of OFDM - An Analysis*, *Telecom Research, Vienna and Ericsson Telecom, Stockholm, 2002*
- [**AT&T Research**], *OFDM Tutorial*, *Red Bank, New Jersey, USA, 1996*
- [**T. Asai, H. Murata, S. Yoshida**], *A study on Differential Coding for Orthogonal Frequency Division Multiplexing*, *IEICE Soc. Conf. '96, Japan, B-440, Sept. 1996.*

- [**A. Tsuzuku, H.Ohta, R.Nakamura**], *A Study of Multipath Interference on OFDM Transmission, Journal of ITE, vol.51, no.9, pp.1493-1503, Sept. 1997.*
- [**F. Sasamori, H. Umeda, S. Handa**], *Approximate Equation of Bit Error Rate in DQPSK/OFDM Systems over Fading Channels*
- [**N. D. Georganas**], *Evaluating of mean error-free intervals of a noisy data channel. IEEE Trans. on Comm., Vol. COM-26, January 1978.*
- [**J. G. Proakis**], *Digital Communications, McGraw Hill Book Company, 1983.*
- [**W. Jakes**], *Microwave Mobile Communications, Wiley and Sons, 1974.*
- [**Vivianne Jodalen et al**], *Military Messaging in IP Networks Using HF Links*
- [**NATO STANAG 4406**], *Military Message Handling System (MMHS), ed. 1, 1999.*
- [**A. Eggen et al**], *The Joint NO and UK Demonstration of Integrated MMHS, PKI and Directory Systems at JWID 2002, FFI/RAPPORT-2002/04655, 2002.*
- [**US MIL-STD-188-141A**], *Interoperability and Performance Standards for Medium and High Frequency Radio Equipment, App. A.*
- [**NATO STANAG 5066**], *Profile for High Frequency (HF) Radio Data Communications*
- [**NATO STANAG 4539**], *Technical Standards for Non-Hopping HF Communications W/form*
- [**NATO STANAG 4538**], *Technical Standards for an Automatic Radio Control System (ARCS) for HF Communications Links*
- [**M. W. Chamberlain and W. N. Furman**], *HF Data Link Protocol Enhancements based on STANAG 4538 and STANAG 4539, Providing Greater than 10 kb/s Throughput over 3 kHz channels, IEE Conf. Pub. No 493, Bath, U.K., 2003, pp. 64–68.*
- [**Application Notes, NC3A**], <http://elayne.nc3a.nato.int>