A TECHNIQUE TO REDUCE CORRELATED ERRORS IN CONTINUOUS MONITORING APPLICATIONS

Zulkarnain Mat Amin

Centre for Industrial Measurement and Engineering Surveys Faculty of Geoinformation Engineering and Science Universiti Teknologi Malaysia 81310 UTM Skudai, Johor, MALAYSIA Email: zulkarnain@fksg.utm.my

David R. Twigg

Department of Civil & Building Engineering Loughborough University Loughborough, Leicestershire, LE11 3TU, UK Email: d.r.twigg@lboro.ac.uk

BIOGRAPHY

Zulkarnain Mat Amin is a lecturer at the Faculty of Geoinformation Engineering and Science, University of Technology Malaysia. He holds a B.Sc. in Surveying Sc. from the University of Newcastle, UK and M.Sc. in Surveying and Mapping from the Curtin University, Australia.

David. R. Twigg is a senior lecturer and leader of the Land Surveying Group at the Department of Civil & Building Engineering, Loughborough University, UK. He holds a Ph.D. from the University of Newcastle, UK.

ABSTRACT

GPS techniques are now being used extensively in many monitoring applications such as engineering structures, landslides and crustal deformation. In most cases, the attainable accuracy of GPS measurements is dependent upon the presence of errors or noises in the measurements. Some of the errors can be eliminated or minimised by differencing techniques, but others require particular attention if a high accuracy result is sought.

This paper presents various experiments on kinematic GPS surveys, from which a method to reduce GPS errors has been established. The method is based on transferring the error from one station to another where the two stations are highly correlated. Three GPS stations were involved: the first was located at a known reference station, the second at fixed station near the object being monitored and the third positioned on the object itself. It is the strong

correlation between the latter stations that enables corrected co-ordinates to be determined.

Results from the tests show that by applying the aforementioned method, the final GPS measurements are more accurate for use with continuous monitoring applications.

Keywords: Continuous Monitoring, Global Positioning System, Correlation and Error Correction.

INTRODUCTION

The Global Positioning System (GPS) is a satellitebased navigation system, which permits users to determine their position in three-dimensional space with a high precision capability. The precision of a few millimetres within a relatively short period of time can be guaranteed to all users through the use of developed techniques in GPS positioning. The principles and techniques of GPS were described in Hofmann-Wellenhof et al, (1997) and Leick (1995). Based on these capabilities, extensive efforts have been made in using GPS for deformation monitoring

Basically, GPS offers two methods for monitoring applications. These can be described as repeated or episodic monitoring and continuous monitoring. In principle, repeated monitoring was accomplished by performing relative positioning at a certain epoch through static surveying technique. By repeating the measurement, any change in the estimated parameter between successive measurements is interpreted as a measure of geometrical displacement. Conversely, in continuous monitoring, the deformable bodies under study were

continuously monitored through the use of two kinematic surveying techniques, i.e. either real time (Real Time Kinematic (RTK)) or post-processing techniques. One of the earliest practical examples of episodic monitoring is to monitor ground vertical movement (Steinberg and Papo, 1988). In this test, the capability of the GPS technique has been combined with conventional surveying technique by forming a mathematical model and adjusted using this combined model. Result show that it is promising in the sense that it can filter out certain errors and is therefore suitable for future application. The use of GPS in the previously mentioned test has been extended to other monitoring application such as dam deformation (Teskey & Porter, 1988), crustal deformation (Kleusberg et. al, 1988 and Hsu, 1996) land subsidence monitoring (Blodgett & Ikehara, 1989), detection of landslide movement (Barbarella et. al, 1989), landslide (Ananga et. al, 1997) and volcanic activity (Abidin et. al, 1998). On the other hand, continuous monitoring activities have included: engineering structures (Ashkenazi, et al 1997, 1998, Brown et. al, 1999, Lovse et. al, 1995, Guo and Ge, 1997), landslides (Kondo & Cannon, 1995 and Shimizu et. al, 1996) and crustal deformation (Genrich & Bock, 1992 and Chen 1998). In this research, the continuous GPS monitoring with kinematic post-processing is emphasized.

The attainable accuracy of GPS measurements are very much dependent upon the presence of errors or noises in the measurements. In general, GPS errors can be listed as below:

- a. Satellite and receiver clock errors.
- b. Satellite geometry.
- c. Satellite orbit.
- d. Atmospheric errors.
- e. Multipath and signal scattering.

A detailed description of these errors can be found in many GPS textbooks (see for example Parkinson & Spilker, 1996, Hofmann-Wellenhof et. al, 1997, Strang & Borre, 1997 and Leick, 1995).

While some of the errors listed above can be eliminated or reduced using GPS positioning techniques, others can be ignored because they are not significant. For example, the results from the tests carried out at Loughborough and by King et. al, (1995) have proven that for short baselines, the use of improved (precise) satellite orbit does not improve the overall estimate in position. The relationship between the error related to the orbit and baseline accuracy can be estimated by the following expression (Wells et, al, 1986),

$$\frac{db}{b} = \frac{dr}{r} \tag{1}$$

where db is the error on the baseline length b, dr is the orbital error and r is the range between GPS receiver and satellite.

The troposphere and ionosphere parts of the atmosphere affect the GPS signal by delaying the time of receipt at the receiver. Trosposheric correction can be determined using different tropospheric models for example Hopfield, Modified Hopfield and Saastamoinen models (Hofmann-Wellenhof et. al, 1997) which are included in the GPS processing software. The ionospheric error on the other hand delays the GPS signal because of the amount of free electrons in ionosphere. This effect is proportional to the total electron content and inversely proportional to the square root of the signal frequency. The total electron content can be measured or estimated, thus one can estimate the ionospheric correction. However, the simplest technique to eliminate this effect is by using a dual frequency receiver i.e. by solving the delay between L1 and L2 a. For single frequency receivers, ionospheric correction is readily available in the navigation message transmitted by satellites.

Multipath affects the control signal in the receiver tracking loops this introduces an error equivalent to ranging errors. Geometrically, low elevation GPS satellites tend to be more susceptible to multipath interference compared to high elevation satellites due to low incident angle. In fact, Barnes et al, (1998) and Jaldelhag et al, (1996) have successfully demonstrated this effect. Furthermore, the multipath effect occurs on a day-to-day basis because the satellite position (or geometry) repeats daily (Leick, 1995). In addition this effect is temporally or spatially dependent upon the site environment. This repetition allows the removal of multipath effect by taking the difference between day-to-day solutions. This procedure has been shown to be viable for removing multipath effect in a permanent continuous GPS network (Chen, 1998). Although those errors are either removed or cancelled by GPS processing techniques, nevertheless, under certain conditions, there may still be errors present in the solution.

For high accuracy positioning applications, such as monitoring of large engineering structures, the most demanding task is to eliminate these errors. Moreover, it is important to identify and remove features that are clearly not due to displacement and to separate between noise and true movement. However, experimental results with continuous monitoring show that many sources of error are highly correlated. Techniques can then be developed to detect and remove common-mode errors. This is one of the scopes investigated in the research.

PRACTICAL WORK AND ANALYSIS

Two tests on kinematic GPS surveys have been carried out in order to achieve the objectives of the study. All the tests were conducted in accordance to different experimental procedures and purposes. A summary of the tests is given in Table 1. The first two of the tests have been mentioned in the previous report but repeated here to show the importance of the results for the ongoing test.

No.	Tests
1	Correlation analysis
2	Error Removal Technique

Table 1: Tests Summary

The data were collected with Leica GPS System receivers operating in stationary mode. The SKI Processing software was used to process the with Microsoft EXCEL and MATLAB software being used for further data analysis. A brief description of the hardware and software used in the tests has been given in the previous report.

Correlation Test

The objective of this test is to examine the association or correlation between two roving stations in kinematic GPS environment. The correlation is the strength of relationship between two sets of random process measured by a correlation coefficient. The correlation coefficient is given by,

$$r = \frac{\sum \left(x - \bar{x}\right) \left(y - \bar{y}\right)}{\sqrt{\left[\sum \left(x - \bar{x}\right)^2 \sum \left(y - \bar{y}\right)^2\right]}}$$
(2)

where *x* and *y* are two sets of random process with mean values of *x* and *y* respectively.

In relative positioning, the GPS observations are highly correlated due to the similarity of the measurement and the environment associated with the observation. This type of correlation is referred to as physical correlation (Hofmann Wellenhoff et.al, 1997) which can be further classified into temporal and spatial correlation The importance of considering temporal correlation on the accuracy estimation has been investigated by El-Rabbany (1994), Han & Rizos (1995) and Robert and Cross (1993).

In the present study, spatial correlation based on two rover stations is determined. If one station was fixed at known position, the accuracy will improve by applying correction to the unknown station. As mentioned earlier, GPS errors such as multipath is highly correlated on day-to-day basis. This indicates that differencing the positions of the same stations on two consecutive days can eliminate this error. Nevertheless, for special applications such as the monitoring of large structures, which requires data in near, or real time, a rigorous error removal technique should be sought. This test undertakes an initial task of investigating this new technique by examining the correlation of two stations, which simultaneously observed the GPS satellites.

The test has been discussed in the previous report but repeated again here to show that there is a significant correlation between two sets of GPS measurements, which eventually provides an indication of the presence of common-mode errors.

Test Description

Two tests with baselines of different sizes have been performed. Four stations (Reference, Rover1, Rover2 and Rover3) have been used to observe the GPS signals (see Figure 1). Table 2 outlines each test giving the selection of reference and roving station and baseline length between roving stations.

Test	Reference	Rover	Baseline
	Station	Station	Length
Short	Reference	Rover1,	1.5 m
Baseline		Rover2	
Long	Reference	Rover2,	3.8 km
Baseline		Rover3	

Table 2: Test Description

During the tests, GPS satellites above an elevation of 15 degrees have been continuously tracked. Each test session consisted of approximately six hours of tracking with measurements of carrier phase recorded once every 15 seconds.



Figure 1: Test Baselines

Results

Table 3 presents correlation coefficients for both baselines. These results are based on the X, Y and Z components of both roving stations. The results show that for short distance between rovers, the measured components are highly correlated, except for Y. In general, the results indicate the presence of correlating errors in the measurements. The results are one argument for establishing an error correction technique, which is discussed in Section 2.4.

	Components		
Baselines	Х	Y	Z
Short	0.764	0.635	0.831
Long	0.479	0.639	0.542

 Table 3: Correlation between Measurements

Error Removal Analysis

The results achieved from the correlation analysis test mentioned above are the key for further analysis in improving position estimates. Using the data from the previous results, it has been shown the technique, which is used in this study, appears to be viable for removing common-mode errors. The technique is based on the application of correction from one roving station to the other roving station, which is simultaneously observing GPS signals. This is only true if the positions of one of the station are known. Then, the difference between the observed and known positions of that station can be written as;

$$c = l_k - l_o \tag{3}$$

where c is the correction parameter, l_k and l_o are the known and observed positions. The corrected positions for other roving stations can be computed by applying the above correction using the expression,

$$X_c = X_o + c \tag{4}$$

where X_c and X_o are the observed and corrected positions respectively.

Using the above technique, the root mean square error (RMSE) of the positions from previous test have been computed and shown in Table 4. The RMSE of the residuals (difference between the known positions and the corresponding observed positions) being computed as

$$RMSE = \pm \sqrt{\frac{\sum_{i}^{n} (x_i - x_k)^2}{n}}$$
(5)

where:

x_i	=	measured positions
x_k	=	known positions
п	=	number of epoch

The table shows the RMSE of the positions before and after applying the correction. From the table, there is almost a 100% improvement of the results using the above technique.

COMPONENTS	RMSE	
	RAW (m)	REDUCED (m)
Х	0.375806	0.068554
Y	0.060851	0.014004
Z	0.491646	0.089768

Table 4: RMSE of Positions

The results shown in Table 4 suggest that the derived procedures can be adopted for removing common mode errors. For this reason, the technique has been used in analysing the results obtained in other simulation tests, which have been executed in conjunction with these tests. The tests involved the construction of a special device, which simulating the movement of the structures Figure 2 illustrates the time series of coordinates before and after applying corrections. The figure also shows the induced translations (Y component) applied to the device.

Conclusions

The investigation has demonstrated the capability of kinematic GPS surveys for the continuous monitoring such as large engineering structures. A crucial finding in the test is the existence of a correlation between two roving stations in the kinematic GPS surveys. Depending on the baseline length and the components of co-ordinates, correlation coefficients of up to 0.831 has been obtained. Evidently, the error removal technique has been established to treat noise in GPS measurements. The technical feasibility of this technique is illustrated through the test conducted on a special apparatus that simulated movement. The test has demonstrated the power of this technique for the improvement of solution estimates. Previous tests on static receivers have shown that an increase of almost 100% in position estimates was achieved by applying this technique

REFERENCES

- Ashkenazi, V., A.H. Dodson, and G.W. Roberts, (1998). "Real-Time Monitoring of Bridges by GPS", in *FIG XXI International Congress*, pp. 503-512, Brighton, England.
- Ashkenazi, V., and G.W. Roberts, (1997). "Experimental Monitoring of the Humber Bridge Using GPS", *Proc. Instn. Engrs. Civ. Engng* (120), 177-182
- Barbarella, M., G. Bitell, G. Folloni, R. Russo, A. Gubellini, and L. Tomassini, (1988).
 "Deformation Surveys of Landslide Using Terrestial Measurements and Space Techniques", in *The 5th Internation FIG Symposium on Deformation Measurements*, New Brunswick, Canada.
- Barnes, J.B., N. Ackroyd, and P.A. Cross, (1998). "Stochastic Modelling for Very High Precision Real-Time Kinematic GPS in an Engineering Environment", in *FIG XXI International Congress*, Brighton, England.
- Blodgett, J., and M.E. Ikehara, (1989). "Monitoring of Land Subsidence in Sacramento Valley, California Using GPS ", *Journal of Surveying Engineering*, 116 (2), 112-130

- Brown, C.J., R. Karuna, V. Ashkenazi, G.W. Roberts, and R.A. Evans, (1999). "Monitoring of Structures Using GPS ", *Proc. Instn. Civ. Engrs Structs & Bldgs*, 134, 97-105
- Chen, X., (1998).Continuous GPS Monitoring of Crustal Deformation with the Western Canada Deformation A X 992-1995, 158 pp., Department of Ge 992-1995, 158 and Geomatics Engineering, University of New Brunswick, New Brunswick.
- Genrich, J.H., and Y. Bock, (1992). "Rapid Resolution of Crustal Motion at Short Ranges with the Global Positioning System ", *Journal of Geophysical Research*, 97 (B3), 3261-3269
- Guo, J., and S. Ge, (1997). "Research of Displacement and Frequency of Tall Building under Wind Load Using GPS", in The 10th International Technical Meeting of the Satellite Division of the Institute of Navigation, pp. 1385-1388, Kansas City.
- Hofmann-Wellenhof, B., and H. Lichtenegger, (1997).*GPS Theory and Practice*, 389 pp., Springer-Verlag, Wien Austria.
- Hsu, P.H., (1996). "The Use of GPS for Monotoring Crustal Deformation", Ph.D. thesis, The University of Nottingham, U.K.
- Jaldehag, R.T.K., J.M. Johansson, and B.O. Ronnang, (1996). "Geodesy Using the Swedish Permanent GPS Network: Effect of Signal Scaterring on Estimates of Relative Side Positions. ", *Journal of Geophysical Research*, 101 (B8), 17841-17860
- Kleusberg, A., Y. Georgiadou, and H. Draget, (1988). "Establishment of Crustal Deformation Networks using GPS: A Case Study ", *CISM Journal*, 42 (4), 341-351
- Kondo, H., and M.E. Cannon, (1995). "Real-time Landslide Detection System using Precise Carrier Phase GPS", in *The 8th International Technical Meeting of the Satellite Division* of the Institute of Navigation 1995, pp. 1877-1884.
- Leick, A., (1995).*GPS Satellite Surveying*, 560 pp., Wiley, New York , Chichester,Brisbane, Toronto and Singapore.
- Lovse, J.W., W.F. Teskey, and G. Lachapelle, (1995). "Dynamic Deformation Monitoring of Tall Structure Using GPS Technology", *Journal* of Surveying Engineering, 121 (1), 35-40
- Parkinson, B.W., and J.J. Spilker, (1996). "Global Positioning System: Theory and Applications Volume 1", in *Progress in* Astronautics and Aeronautics, pp. 793, American Institute of Aeronautics and Astronautics, Inc., Washington, USA.

- Shimizu, N., Y. Mizuta, H. Condo, and H. Ono, (1996). "A New GPS Real-Time Monitoring System for Deformation Measurements and its Application", in 8th Internation FIG Symposium on Deformation Measurements, pp. 47-54, Hong Kong.
- Steinberg, G., and H.B. Papo, (1988). "Survey of Vertical Deformation by GPS and Precise Levelling", in 5th Internation FIG Symposium on Deformation Measurements, New Brunswick, Canada.
- Strang, G., and K. Borre, (1997).*Linear Algebra*, *Geodesy, and GPS*, 624 pp., Wellesley-Cambridge Press, Wellesley, USA.
- Teskey, W.F., and T.R. Porter, (1988). "An Integrated Method for Monitoring the Deformation Behavior of Engineering Structures", in 5th Internation FIG Symposium on Deformation Measurements, New Brunswick, Canada.
- Wells, D.E., N. Beck, D. Delikaraoglou, A. Kleusberg, E.J. Krakiwsky, G. Lachapelle, R.B. Langley, M. Nakiboglu, K.P. Schwarz, J.M. Tranquilla, and P. Vanicek, (1987). *Guide to GPS Positioning*, Canadian GPS Associates, New Brunswick, Canada.



Figure 2: Comparison of Raw and Reduced Positions