

**THERMAL ANALYSIS OF H.V INSULATION OIL DURING PARTIAL
DISCHARGE DETECTION**

RASOOL ABDEFADIL GATEA

UNIVERSITI TEKNOLOGI MALAYSIA

THERMAL ANALYSIS OF H.V INSULATION OIL DURING PARTIAL
DISCHARGE DETECTION

RASOOL ABDEL FADIL GATEA

A project report submitted in partial fulfilment of the
requirements for the award of the degree of
Master of Engineering (Electrical-Power)

Faculty of Electrical Engineering
Universiti Teknologi Malaysia

DECEMBER 2014

To my God, Allah ‘azza wa jalla
Then to my beloved mother, family, and all my friends

ACKNOWLEDGEMENT

Thanks to Allah SWT for everything I was able to achieve and for everything I tried but I was not able to achieve.

I am grateful for several people for making this thesis possible. I would like to begin by expressing my deep appreciation to my supervisor, Associate Prof. Dr. Mohd Muhridza Bin Yaacob for his guidance and encouragement. Despite the busy schedule, he has provided me with valuable ideas, advice and comments. I am very fortunate to have him as my adviser. Special thanks to my colleagues for valuable comments and suggestions. I would like to thank all my friends for personal support.

My family receives my deepest gratitude and love for their patience and support during the years of my study.

ABSTRACT

Historically, the arc discharge analyzing technique was one of the first methods to determine the status of the insulation oil. Due to the harsh environment and the continue usage of the high voltage transformers, many problems of insulation can be produced leading to the failure of the transformer. The problem of the thesis is to find the best available solution to conduct real time analyzing of insulation oil of high voltage transformers, so that the high voltage transformer can be safeguarded from failure in the most effective and economic manner. In this work, the temperature of the insulation oil will be captured and calculated with and without partial discharge occurring. The simulated arc discharge is generated using 7.5 kV power source in two round shape steel electrodes having 5 mm gap. This distance (between the sensor and arc discharge source) is set at 5 cm. The infrared thermometer (laser gun) was used to capture the insulation oil temperature by sending a laser light toward the insulation oil and that light will be reflected back and received by the device and then the temperature of the oil will be captured and measured. This study will help to predict the insulation oil age of high voltage transformers, which reduce the maintenance cost of high voltage transformer.

ABSTRAK

Menurut sejarah, teknik menganalisis pelepasan arka adalah satu daripada kaedah pertama untuk menentukan status minyak penebat. Oleh kerana persekitaran yang sukar dan penggunaan yang berterusan daripada transformer voltan kuasa tinggi, banyak masalah penebat boleh dihasil membawa kepada kegagalan transformer. Masalah kajian adalah untuk mencari penyelesaian terbaik untuk menjalankan analisis masa sebenar minyak penebat transformer voltan kuasa tinggi supaya transformer voltan kuasa tinggi dapat dilindungi daripada kegagalan dengan cara yang paling berkesan dan ekonomi. Dalam kajian ini, suhu minyak penebat akan diambil dan dikira dengan dan tanpa pelepasan separa yang berlaku. Discaj arka simulasi dihasilkan menggunakan sumber kuasa 7.5 kV dalam dua elektrod keluli bentuk bulat yang mempunyai jurang 5 mm. Jarak (antara sensor dan pelepasan arka sumber) ditetapkan pada 5 cm. Termometer infra merah (pistol laser) telah digunakan untuk menangkap suhu minyak penebat dengan menghantar cahaya laser ke arah minyak penebat dan cahaya tersebut akan dipantulkan semula dan diterima oleh peranti dan kemudian suhu minyak itu akan ditangkap dan diukur. Kajian ini akan membantu untuk meramalkan umur minyak penebat bagi transformer voltan kuasa tinggi, yang mengurangkan kos penyelenggaraan transformer voltan kuasa tinggi.

TABLE OF CONTENTS

CHAPTER	TITLE	PAGE
	DECLARATION	ii
	DEDICATION	iii
	ACKNOWLEDGEMENT	iv
	ABSTRACT	v
	TABLE OF CONTENTS	vi
	LIST OF FIGURES	ix
1	INTRODUCTION	1
	1.1 Overview	1
	1.2 Background	2
	1.3 Problem Statement	4
	1.4 Objectives	5
	1.5 Scope of Work	5
	1.6 Thesis Organization	6
2	LITERATURE REVIEW	7
	2.1 Introduction	7
	2.2 Sensors for the Detection of PD Phenomenon	8
	2.2.1 The Sensors for Electrical Quantity Measurement	8
	2.2.2 The Sensors for Acoustic Detection	10
	2.2.3 The Sensors for Optical Detection	11
	2.3 PD Detection Process	13

2.3.1	Electrical detection	13
2.3.1.1	UHF PD Detection in Power Cable	13
2.3.1.2	UHF PD Detection in GIS	15
2.3.1.3	UHF PD Detection in Transformer	16
2.3.2	Chemical Detection	18
2.3.2.1	Chemical Detection of PD in Transformers	18
2.3.3	Acoustic Detection	19
2.3.3.1	Acoustic Technique for the Detection of PD in GIS	20
2.3.3.2	Acoustic Technique in the Detection of PD for an Oil Cooled Transformer	21
2.3.3.3	Acoustic Technique to Detect PD in HV Cable	22
2.3.4	Optical Detection	23
2.3.4.1	Optical Detection of PD in Transformer Using Mach–Zehnder Interferometers	24
2.3.4.2	Optical Detection of PD in Transformer Using Fabry–Perot Interferometric Sensor	25
3	RESEARCH METHODOLOGY	27
3.1	Introduction	27
3.1.1	Detection of Acoustic Wave Emission Induced by PD using PZT and FOS Sensors Simultaneously	28
3.2	Calculation of Insulation Oil Temperature	30
3.3	Equipment of Experimental Work	31
3.3.1	Light Source	31

3.3.2	Photo Diode (BPX65)	32
3.3.3	The Multimode Fiber Step-Index (MMF-SI)	33
3.3.4	Photodiode Amplifier	33
3.3.5	Piezo Film Sensor Element	34
3.3.6	Oscilloscope	36
3.3.7	Infrared Thermometer	36
4	RESULT AND DISCUSSION	38
4.1	Introduction	38
4.1.1	Detection of Acoustic Wave Emission Induced by PD using PZT and FOS Sensors Simultaneously	38
4.2	The Analysis of the Insulation Oil Temperature	40
5	CONCLUSION	42
	REFERENCES	44

LIST OF FIGURES

FIGURE NO	TITLE	PAGE
2.1	(a) UHF sensor adapted to a GIS grounding bar. (b) Directional coupler implemented in a cable joint. (c) Oil valve sensor for power transformer reactor e.g. left side for usage on DN 50 gate valve right side for DN 80 gate valve. (d) Inductive UHF sensor for power cable termination	9
2.2	Three types of UHF sensors: disc-type, monopole-type and spiral-type	10
2.3	Diagram of a capacitive coupler	10
2.4	(a) Piezoelectric film sensor with his connector. (b) Typical design of piezoelectric transducer sensor	11
2.5	(a) Optical fiber intrinsic sensor based on Mach-Zehnder fiber interferometers. (b) Intrinsic multimode optical fiber sensor	12
2.6	(a) Extrinsic Fapry-Perot interferometer sensor. (b) Extrinsic micro electro-mechanical system sensor	12
2.7	Plug-in cable termination and principle of the UHF PD diagnostics	14
2.8	UHF PD sensor connected at high voltage-and-extra high voltage-termination	15
2.9	Measurement equipment and a typical GIS test chamber	16

2.10	Principle of a Typical UHF of PD Monitoring System	17
2.11	Simplified diagram of a typical high voltage system with PD detector	17
2.12	(a) Hydrogen–oil- detector. (b) Hydrogen-in-oil detector 2 Continuous monitoring	19
2.13	GIS practical implementation with contact sensor	20
2.14	Configuration of the experimental apparatus	22
2.15	Acoustic sensor was bounded with cable joint	23
2.16	Experimental set up for detection of PD generated in laboratory condition using Mach–Zehnder interferometer	25
2.17	Illustration of principle of Fabry–Perot interferometric sensor	26
3.1	Flowchart of methodology	28
3.2	Schematic setup for detection of acoustic emission phenomenon	29
3.3	Experimental setup of work in an oil tank	30
3.4	Photo of light source	31
3.5	Spectra output of light source	31
3.6	Photo of photodiode	32
3.7	Spectral sensitivity of photodiode	32
3.8	Wavelength of MMF-SI	33
3.9	Photo of photodiode amplifier	34
3.10	Frequency response of the sensor	35
3.11	Photo of oscilloscope	36
3.12	The Infrared Thermometer	37
4.1	Time domain: (a) The captured partial discharge signal from the FOS sensor (b) The captured partial discharge signal from the PZT	39
4.2	The temperature time curve with PD	41
4.3	The temperature time curve without PD	41

LIST OF SYMBOLS

Λ	-	Wavelength
$P(\lambda)$	-	Spectral power distribution of optical signal
$R(\lambda)$	-	Output response of optical signal
SF_6	-	Sulfur hexafluoride
C_a	-	Capacitance of the test object which is not affected by any PD
C_b	-	Stray capacitance of the PD source
C_c	-	Internal capacitance of PD source
∂n	-	Change in refractive index
Pe	-	Effective photoelastic constant
P	-	Applied pressure
E	-	Young's Modulus
I	-	Interaction length
$\partial\Phi$	-	Phase change

LIST OF ABBREVIATIONS

PD	-	Partial discharge
μm	-	Micro meter
μS	-	Micro second
AC	-	Alternative voltage
AE	-	Acoustic emissions
B	-	Blue
CH	-	Channel
CIE	-	International commission on illumination
Cm	-	Centimeter
CPT	-	Center for photonics technology
D	-	Dominant wavelet
dB	-	Decibel
DC	-	Direct current
DGA	-	Dissolve gas analysis
DWT	-	Discreet wavelet transform
EHV	-	Extra high-voltage
EMI	-	Electro-magnetic interference
EPIR	-	Electrical power research institute
F	-	Frequency
FFT	-	Fast Fourier transform
FOS	-	Fiber optical sensors
G	-	Green
GHz	-	Giga hertz
GI	-	Graded index

CHAPTER 1

INTRODUCTION

1.1 Overview

The strong electric field has some hidden mysteries that appear as electrochemical and plasma-chemical reactions around the high voltage appliances like cables and transformers. One of the mysterious phenomenon is small electrical sparks that are present in an insulation medium which deteriorates the material as a result insulation becomes weak to sustain that high voltage and causes electrical breakdown. In case of cables, the entrapped gas condition in void spaces of the medium is the root cause of this phenomenon which changes the electro-physical nature of the medium. In case of power transformers, high non-uniform electric field is present near the vicinity of devices which produce degradation and aging effect for insulators. This micro discharge activity near the high voltage devices is called partial discharge (PD) phenomenon which generates energy that can be measured and used for the diagnostic and monitoring study of power transformer before complete failure [1]. The PD emitted energy as electromagnetic emission, acoustic emission and ozone and nitrous oxide gases. We can use this emitted energy to detected PD signal [2]. High Voltage equipment and High Voltage installation owners have come to terms with the need for conditions monitoring process of PD in equipment such as power transformers, gas insulated substations (GIS) and cable installations [3]. The detector locates the site of PD by studying the amplitude

attenuation or phase delay of the acoustic waves. PD generates mechanical wave (acoustic wave) which is propagated in a radial manner along the medium from the site of discharge. The acoustic wave is produced by the explosion of mechanical energy due to the vaporization of material inside the transformer tank forming a pressure field [4],[5],[6],[7],[8]. The optical fiber sensor can measure a wide range of chemical and physical parameters due to its small size, high sensitivity, light weight, high frequency response and immune electromagnetic interference. Optical fiber acoustic sensors has been shown advantages in many applications, such as underwater hydrophones civil structure non-destructive diagnosis, material property analysis [9] traffic monitoring and vehicle detection and PD detection[10]. Usually, optical detection technique is based on fiber optic intrinsic interferometers such as Michelson interferometers, Mach–Zehnder interferometers, multimode fiber and fiber optic extrinsic such as Fabry–Perot interferometric sensors. The Michelson interferometers, Mach–Zehnder interferometers sensors were suffer from the fringe fading problems due to random polarization rotation. Fabry–Perot interferometric sensors are compact in size compared to Michelson and Mach–Zehnder fiber sensors, and therefore achieve virtually single-point measurement. But until now, using an optical method in PD detection has limitation due to measurements sensitivity of sensors are not enough for PD detection. In this study detection of PD using step-index MMF has been done. Also analysis of breakdown arc in insulation oil is described.

1.2 Background

Electrical power transformers is usually the most critical and costly component in power transmission and distribution systems. The failure rate of extra high-voltage (EHV) power transformers is as high as 3% per year per device, which results in the loss of tens of millions of dollars for each failed unit due to serious insulation oil spills resulting in major disruption of service [11].

PD is reported to be involved in all transformer insulation failure. It can degrade electrical insulation and eventually lead to failure of the transformer. Therefore, it is important to monitor the partial discharge activity in a transformer in order to detect incipient insulation problems, and to prevent further catastrophic failure. One of the methods of monitoring PDs is to detect the acoustic waves they generate. An obvious advantage of the acoustic method is that it can locate the site of PD from the phase delay or the amplitude attenuation of the acoustic waves. Piezoelectric acoustic sensor is typically used for realizing PDs while being mounted externally on the walls of the power transformer. The external method offers the advantage of easy installation and replacement. However, piezoelectric sensors often suffer from corruption of the signal due to environmental disturbances such as electro-magnetic interference (EMI). Another problem associated with the externally mounted piezoelectric sensors is that the multi-path of the acoustic wave transmission makes it difficult to locate the exact site of the PD. It is thus desirable to have sensors that can be reliably operated inside a transformer, even within the transformer windings, with high enough pressure sensitivity and frequency response (up to 1 MHz) to pick up PD induced acoustic signals. The sensor should also be sensitive to the direction of the acoustic wave from which the location source of the PD can be recovered. These sensors need to be chemically inert, electrically non-conducting, and small in size. An optical fiber-based sensor is an attractive set-up to measure a wide range of physical and chemical parameters because of its small size, light weight, high sensitivity, high frequency response, and immunity to electromagnetic interference.

Electrical Power Research Institute (EPRI), the Center for Photonics Technology (CPT) at the Bradley Department of Electrical and Computer Engineering are currently leading the effort in developing novel fiber-based sensors that can provide the desirable sensitivity and frequency response for real-time on-line detection of acoustic emissions (AE) in power transformers [12-14]. In previous research on PD, the discharge was detected using a tube to listen for any ticking or hissing generated by PD within the tank [15,16]. In 1771, Lichtenberg detected PD and wrote an experimental report on his discovery. In 1873, Maxwell extended the work of Lichtenberg by designing instrumentations for electrical PD detection and

created fundamental relevance of physical models for better understanding of complex PD phenomena. The hypothesis of MAXWELL on the existence of electromagnetic waves and their propagation in space and time was demonstrated with an impressive experiment by Hertz. In 1919, SCHERING developed the first loss factor bridge for the electrical measurements of PD. This instrument continued to be a useful device for this purpose until 1924. The radio frequency was used to recognize the character of corona discharges in 1925 by SCHWAIGER. One method that can be employed to detect PD is by measuring the properties of radio interference (radio interference voltage-RIV) generated by the random corona discharges. This technique was first used by DENNHARD in 1937 and is still being used widely today. The equivalent circuit method for the assessment of PD losses under AC stresses was introduced by BYRSTLYN in 1928 [17]. In 1932, his technique was systematically investigated by GEMANT and PHILIPPOFF with the aid of oscillographic techniques to ascertain the sequence of discharge events per cycle of the applied AC voltage [18].

1.3 Problem Statement

Due to the harsh environment and the continuing usage of the high voltage transformers, many problems of insulation can be produced leading to the failure of the transformer. The primary methods of PD detection are based on the observable electric and acoustic characteristics of the phenomenon. Acoustic PD detection systems are more favorable than electric systems in transformer monitoring. The problem with current acoustic PD detection systems is that the acoustic signal must be observed outside of the transformer tank because there are no developed sensors that can survive the environment of the tank interior and be electrically and chemically neutral. Because the path between a PD and the acoustic sensors includes the wall of the tank, multi-path interference can severely limit the accuracy of any positioning system. The interference is caused by the differing acoustic velocity of the wave in the oil and the transformer tank. Therefore, it would be an enormous

advantage if a sensor could be designed to operate within the transformer tank without inhibiting or changing the functionality of the transformer.

In the absence of the insulation diagnostics many transformer failed before reaching their designed technical life. The failure of such transformer costs several million dollars either to repair or to replace. In high voltage power apparatus one of the most common liquid insulating materials used for insulation is the transformer oil. Degradation of transformer oil is due to the combination of the ageing processes such as thermal ageing, electrical arcing and partial discharge (PDs) while it is under operation during its long period of service. The insulating oil of HV equipment is degraded due to the combination of the ageing processes such as electrical arcing, thermal ageing and oxidation while it is operating in long period of service. Apart from the ageing process as described above, partial discharges are also responsible for insulation degradation process [19, 20]

1.4 Objectives

1. To Detect of partial discharge in insulation oil using optical sensor and acoustic sensor
2. To Calculate the insulation oil temperature during partial discharge

1.5 Scope of Work

1. Detection of partial discharge in transformer oil
2. Calculation of insulation oil temperature
3. Detection of partial discharge signal using optical and acoustic technique

1.6 Thesis Organization

The thesis consists of five chapters, organized as following:

- Chapter one in this research presents an overview as a whole. The background, problem statement, objectives and scope have been described.
- In chapter two literature review of arc discharge have been described.
- In chapter three, the experimental set-ups and procedures employed and the equipment in this study are described.
- In chapter four present the result and discussion of experimental work.
- Finally, chapter five will contains the conclusion of the main finding of this work.

REFERENCES

- [1] Yaacob, M. M., Alsaedi, M. A., Rahman, R. A., Bidin, N. and Maqbool, W. 2013. Detection and Wavelet Analysis of Acoustic Emission Signal from Partial Discharge Captured by Multimode Optical Fiber and Piezoelectric Sensors in Insulation Oil. *International Journal of Physical Sciences*, vol. 8, no. 21, pp. 1149–1160.
- [2] Yaacob M. M., Alsaedi M. A., Al Gizi A., and Zareen N. 2013. Partial Discharge Signal Detection using Ultra High Frequency Method in High Voltage Power Equipments : A Review. *International Journal of Scientific & Engineering Research*, vol. 4, no. 1, pp. 1–6.
- [3] Yaacob M. M. and Alsaedi, M. A. 2012. Review on Partial Discharge Detection Techniques Related to High Voltage Power Equipment Using Different Sensors. *Archives Des Sciences*, vol. 65, no. 9, pp. 659–676.
- [4] Harrold, R. T. 1985. Acoustical Technology Applications in Electrical Insulation and Dielectrics. *IEEE Transactions on Electrical Insulation*. Vol., vol. EI-20, no. 1, pp. 3–19.
- [5] Lundgaard L. E. and Electric, N. 1992. *Acoustic Partial Discharge Detection - Fundamental Considerations*. pp. 25–31,.
- [6] Varlow B. R., Auckland D. W., Smith C. D., and Zhao J. 1999. *Acoustic Emission Analysis of High Voltage Insulation*. vol. 146, no. 5.
- [7] Harrold, R. T. 1979. Acoustic Waveguides for Sensing and Locating Electrical Discharges in High Voltage Power Transformers and Other Apparatus. *IEEE Transactions on Power Apparatus and Systems*. vol. PAS-98, no. 2, pp. 449–457.

- [8] Mats Leijon, L. M. and T. B. 1992. PD Source Identification in Solids. Conference Record of *the 1992 IEEE International Symposium on Electrical Insulation*, Baltimore, MD USA., pp. 415–418.
- [9] Greene, K. A. M. and R. O. C. J. A., Tran T A, Bhatia V, Gunther M F, Wang A. 1995. Optical Fiber Sensing Technique for Impact Detection and Location in Composites and Metal Specimens. *IOPscience*, vol. 4, no. 2, pp. 93–99.
- [10] Furstenau N., Schmidt M., Horack H., Goetze W., Schmidt, W. 1997. Extrinsic Fabry-Perot Interferometer Vibration and Acoustic Sensor Systems for Airport Ground Traffic Monitoring. *IEE Proc -Optoelectron*, vol. 144, no. 4, pp. 134–144.
- [11] Pledger W.A and Pyke S. C. Gas Monitor Update: Review of Progress in the Development of an Automated Transformer Oil Monitor (ATOM). in *EPRI Substation Equipment Diagnostics*, 1994.
- [12] Xiao A. W. H., Deng J., Huo W., Luo M., Wang Z., May R. G., Thin Silica Diaphragm- based SCIIB Fiber Optic Acoustic Sensors. in *Harsh Environment Sensors*, 1999, p. 3852.
- [13] Deng J. D., Xiao H., Wang A. Optical fiber Sensor-based Detection of Partial Discharges in Power Transformers. *Opt. Laser Technol. Vol 33, n*, vol. 33, no. 5, pp. 305–311, 2001.
- [14] Yu B, Kim D.W, Deng J, Xioa H and Wang A. Fiber Fabry-Perot Sensors for Detection of Partial Discharges in Power Transformers, *Applied Opt.*, vol. 42, no. 16, pp. 3241–3250, 2003.
- [15] Hawley R. and Jiniswale S., *Measuring Partial Discharges*,. London: R. Hawley and S. Jiniswale. (1964). Measuring Partial Discharges,. London., 1964.
- [16] Kreuger, EH. *Discharge Detection in High Voltage Equipment*. London: Temple Press Books, 1964.
- [17] Bursteyn, *The Losses in Layered Dielectrics*. pp. 1258–1291, 1928.
- [18] Gemant, A. and von Philipoff. *The Spark Gap with Precondenser*. vol. 13, pp. 425–430, 1932.
- [19] Karmakar, S., Roy, N. K., & Kumbhakar, P. (2009). Detection of Partial Discharges in a High Voltage Equipment. *J. Electr. Eng*, 9(2), 26-31.

- [20] Karmakar, S., Roy, N. K., & Kumbhakar, P. (2009). Monitoring of High Voltage Power Transformer using Direct Optical Partial Discharge Detection Technique. *Journal of Optics*, 38(4), 207-215.
- [21] Markalous S. M., Ring Z., Tenbohlen S., and Feser K. 2008. Detection and Location of Partial Discharges in Power Transformers using Acoustic and Electromagnetic Signals.
- [22] Pinpart T. and Judd, M. D. 2009. Experimental Comparison of UHF Sensor Types for PD Location Applications. no. June, pp. 26–30.
- [23] Tian, A. E. D. Y., Lewin, P.L. 2002. Comparison of on-line Partial Discharge Detection Methods For HV Cable Joints. *IEEE Transaction on Dielectric and Electric Insulation*, pp. 604–615,
- [24] Dukes, R., Culpan, E. A. and C. Eng. 1984. Acoustic Emission : Its Techniques and Applications. vol. 131, no. 4.
- [25] Lamela-Rivera H., Maci-Sanahuja C., and Garca-Souto J. a, 2003. Detection and Wavelet Analysis of Partial Discharges using an Optical Fibre Interferometric Sensor for High-Power Transformers. *J. Opt. A Pure Appl. Opt.*, vol. 5, no. 1, pp. 66–72.
- [26] Cosgrave J., Vourdas, G. R., Jones, J. W., Spencer, M. Murphy M., and Wilson. 1993. Acoustic Monitoring of Partial Discharges in Gas Insulated Substations using Optical Sensors. *IEE Proc. A Sci. Meas. Technol.*, vol. 140, no. 5, p. 369.
- [27] Jiangdong. Deng A. W. and Y. L., Hai Xiao, Wei Huo, Ming Luo, Russell G. May. 2001. Optical Fiber Sensor-based Detection of Partial Discharges in Power Transformers. *Opt. Laser Technol. Vol 33, n*, vol. 33, no. 5, pp. 305–311.
- [28] Huecker, T. 1998. Application of UHF Partial Discharge Monitoring and Expert System Diagnosis. pp. 61–64.
- [29] Judd M. D. 1998. High Bandwidth Measurement of Partial Discharge Current Pulses. pp. 436–439.
- [30] Boltze M., Markalous S. M., Bolliger A., Ciprietti O., Chiu J. 2009. On-Line Partial Discharge Monitoring and Diagnosis at Power Cables. in *In: proceeding of Electrical Insulation*.

- [31] Sarathi R., Giridhar V., and Sethupathi K. 2010. Analysis of Partial Discharge Activity by a Conducting Particle in Liquid Nitrogen under AC Voltages Adopting UHF Technique. *Cryogenics (Guildf)*., vol. 50, no. 1, pp. 43–49.
- [32] Shen Z. B. and Member S. 2006. Localization of Partial Discharges Using UHF Sensors in Power Transformers. pp. 1–6.
- [33] Kemp I. J. J. 1995. Partial Discharge Plant-Monitoring Technology: Present and future Developments. *IEE Proc. - Sci. Meas. Technol.*, vol. 142, no. 1, p. 4.
- [34] Belanger G. and Duval, M. 1977. Monitor for Hydrogen Dissolved in Transformer Oil. *IEEE Trans. Electr. Insul*, vol. 69, no. 5, pp. 334–340.
- [35] Kil G.-S., Kim I.-K., Park D.-W., Choi S.-Y., and Park C.-Y. 2009. Measurements and Analysis of the Acoustic Signals Produced by Partial Discharges in Insulation Oil. *Curr. Appl. Phys.*, vol. 9, no. 2, pp. 296–300.
- [36] Conference A. R., Insulation E., Phenomena D., and Engineering H. V. 2008. Review of Partial Discharge Monitoring Techniques used in High Voltage Equipment. pp. 400–403.
- [37] Macià-Sanahuja C., Lamela H., and García-Souto J. a., 2007. Fiber optic Interferometric Sensor for Acoustic Detection of Partial Discharges. *J. Opt. Technol.*, vol. 74, no. 2, p. 122.
- [38] Search H., Journals C., Contact A., Iopscience M., Mater S., and Address I. P., 1992. Extrinsic Fabry-Perot Sensor for Strain and Crack Opening Displacement Measurements from - 200 to 900 degrees C. *IOPscience*, vol. 237, pp. 237–242.
- [39] Unnikrishnan V. K., Alti K., Kartha V. B., and Santhosh C., 2010. Measurements of Plasma Temperature and Electron Density in Laser-Induced Copper Plasma by Time-Resolved Spectroscopy. vol. 74, no. 6, pp. 983–993.
- [40] Sansonetti J. E. 2005. Handbook of Basic Atomic Spectroscopic Data. *Journal of Physical and Chemical Reference Data*. vol. 34, no. 4, p. 1559.