

# WIRELESS NOTIFICATION SYSTEM FOR THE HEARING IMPAIRED

MURNIWATI BT ANWAR

A project report submitted in partial fulfillment of the  
requirements for the award of the degree of  
Master of Engineering (Electrical – Mechatronic & Automatic Control)

Faculty of Electrical Engineering  
Universiti Teknologi Malaysia

MAY 2007

To my beloved husband, parents, children

And to my dear friends

## **ACKNOWLEDGEMENT**

In the name of Allah, the most Beneficent and most Merciful.

I would like to express my personal and sincere gratitude to my project supervisor Professor Dr. Ruzairi for his kind encouragement, understanding and believing on me to complete this project. May Allah bless and reward prof. Thanks to my husband Abdul Rahman, parents Mr Anwar Satar, Mrs Djanimar and all my family members for their continued love, supportive, understanding and motivation.

Special appreciation goes to my Mfi colleagues for helping me throughout the development of the project and moral support. May Allah bless and reward them for their sincere endeavor and contribution in the way of knowledge.

Thank you also to all lecturers, staffs, friends and all who has directly and indirectly involved in the production of this project. Your helps and cooperation will never be forgotten.

## **ABSTRACT**

Wireless notification system for hearing impaired is a prototype of home notification system dedicated for the hearing impaired people that can fulfill five basic and important notification or alert system namely; house on fire, baby's crying, burglar alarm notification system, door bell ringing and when it starts raining. All the signals wired to the main controller unit and transmit via wireless system to the wrist alert unit or wristband device. The hearing impaired people will be notified the daily important situations and events happen in the house using vibrator and LCD display module. Moreover the system able to differentiate the priority level of the signals and also notify the neighbours if an emergency occurs such as the house on fire.

## **ABSTRAK**

Sistem pemberitahuan tanpa wayar untuk cacat pendengaran adalah suatu sistem untuk memberitahu situasi yang berlaku di rumah kediaman khusus untuk mereka yang cacat pendengaran dimana ia meliputi lima jenis isyarat penting untuk diberitahu kepada pengguna iaitu bila rumah tersebut terbakar, bayi menangis, terdapat pencerobohan atau kecurian berlaku, situasi dimana ada yang menekan butang loceng pintu dan apabila hujan mula turun. Kesemua isyarat ini disambungkan kepada unit pengawal utama dan isyarat ini dihantar ke unit pemberitahu yang dipasang di lengan orang cacat pendengaran menggunakan system tanpa wayar. Alat gelang ini akan bergetar dan memaparkan situasi yang berlaku menerusi module paparan LCD. Alat ini juga dapat membezakan kepentingan isyarat yang masuk dan dapat mengeluarkan isyarat untuk memberitahu kepada jiran tetangga jika terdapat situasi kecemasan seperti kebakaran.

## TABLE OF CONTENTS

CHAPTER	TITLE	PAGE
		i
	DECLARATION	ii
	DEDICATION	iii
	ACKNOWLEDGEMENTS	iv
	ABSTRACT	v
	ABSTRAK	vi
	TABLE OF CONTENTS	vii
	LIST OF TABLES	xi
	LIST OF FIGURES	xiii
	LIST OF ABBREVIATIONS	xvi
	LIST OF APPENDICES	xvii
1	INTRODUCTION	1
	1.1 Overview	1
	1.2 Objectives	2
	1.3 Scopes of work	3
	1.4 Project Background	3
	1.5 Expected result	4

<b>2</b>	<b>LITERATURE REVIEW</b>	<b>5</b>
2.1	Hearing impaired	
2.2	Hearing loss	5
2.3	Assistive Listening Device ( ALD )	6
2.4	Wireless – Radio Frequency	8
2.5	In door RF propagation	9
2.6	Several Researches on hearing impaired	10
		12
<b>3</b>	<b>PROJECT METHODOLOGY</b>	<b>14</b>
3.1	Project overview	
3.2	Main Controller and the Interfacing	14
	Components	16
3.3	Wrist alert unit	
3.4	RF Encoder PT 2262 and Decoder PT 2272	24
3.4.1	Encoder PT2262	27
3.4.2	Decoder PT2272	28
3.4.3	Testing the transmitter ( Encode )and Receiver (Decode) module.	29 31
3.5	Programming	
3.5.1	Programming PIC 16F84A using Flow Code	32 32
3.5.4	Programming the Main Controller Unit	
3.5.5	Program The Wrist Alert Unit	37
		43
3.6	Power Supply Consideration	46
3.7	Antenna	48

<b>4</b>	<b>ANALYSIS AND TEST RESULT</b>	<b>49</b>
4.1	Circuit analysis	49
	4.4.2 Baby cry detection circuit	49
	4.4.2 Temperature sensor	51
	4.4.2 Rain detector sensor	52
	4.4.2 Door bell detector	52
	4.4.2 Burglar alarm sensor	53
4.3	Testing sensors individually	55
	4.4.2 Testing the baby cry sensor module	55
	4.4.2 Testing temperature sensor	57
	4.4.2 Testing door bell module	58
	4.4.2 Testing burglar alarm module	58
	4.4.2 Testing rain detector	60
4.4	Testing the Integration of Sensor Modules with Main Controller and Communication with Wrist Alert Unit.	61
4.5	Testing On The Performance Of 433.9 Mhz Rf Module	64
	4.4.2 Testing RF Inside The House	65
	4.4.2 Testing In An Open Area	71
4.6	Observation And Discussions.	73



<b>5</b>	<b>CONCLUSION AND RECOMMENDATION</b>	<b>74</b>
5.1	Conclusion	74
5.2	Future work improvement and recommendation	75 75
	<b>REFERENCES</b>	<b>77</b>
	<b>APPENDICES</b>	<b>78</b>

## LIST OF TABLES

<b>TABLE NO</b>	<b>TITLE</b>	<b>PAGE</b>
2.1	Hearing loss according to dB range	5
2.2	Relation of attenuation and materials	12
3.1	Suggested oscillator resistor for encoder and decoder	18
3.2	Sensor contact input address in Port A	20
3.3	Data input read by the microcontroller	20
3.4	Three bit coded data corresponds with the input signals	22
3.5	Sensor relay connection pin on the connector	22
3.6	Output LCD display corresponds to the input data received by microcontroller.	24
3.7	Testing result of encode and decode 3 bit data using RF transmission	31
3.8	Functions of each routine in the main controller flow chart	38
3.9	Function of each routine in the flow chart for wrist alert unit	43
4.1	Testing result on burglar detection sensor	56

4.2	Test result on burglar detection module	59
4.3	Integration and communication testing procedure of Sensors, main controller and wrist alert unit	62
4.4	Testing RF module performance procedure	68
4.5	Test result when transmitter and Receiver at 1st floor	69
4.6	Test result when transmitter at 1st floor and receiver at 2nd floor	70
4.7	Test result transmitter and receiver at 2nd floor	71
4.8	Test result in an open and still area	72
4.9	Test result in an open and windy area	72

**LIST OF FIGURES**

<b>FIGURE NO.</b>	<b>TITLE</b>	<b>PAGE</b>
2.1	Ear major parts	6
2.2	Electromagnetic waves	10
3.1	Block diagram of the system	15
3.2	General view of the system	16
3.3	TWS-434 transmitter	17
3.4	RWS-434 Receiver	18
3.5	Main controller circuit	21
3.6	All sensor relay connection	23
3.7	The PCB layout of the main controller	23
3.8	Wrist Alert circuit	25
3.9	Interfacing components on wrist alert unit	26
3.10	Complete wrist alert units.	26
3.11	Wrist alert drawing.	27
3.12	Block diagram of PT2262 encoder	28
3.13	PT2272 Decoder block	29
3.14	PT2272 decoder flow chart diagram	30

3.15	Testing the transmitter and receiver module	32
3.16	The development board block diagram.	33
3.17	Build the program by drag and drop from the toolbar.	34
3.18	Choosing the target PIC	34
3.19	Choosing the oscillator frequency	34
3.20	Selection type of oscillator circuit	35
3.21	Simulation on displaying Hello world on LCD	36
3.22	Select the type of compilation	36
3.23	Flow chart of proposed control unit.	39
3.24	Flow chart of the wrist alert unit program	42
3.25	Reduce and regulate supply voltage from lithium battery	47
3.26	Reduce and regulate supply voltage from battery 9 V alkaline battery	47
3.27	Three type of battery being used which are alkaline battery lithium battery and an adaptor.	48
3.28	Extendable antenna where the length can be extended to 160cm	48
4.1	Baby cry detection circuit	50
4.2	Temperature sensor module	51
4.3	Rain detector sensor modules	52
4.4	Door bell module	53
4.5	Burglar alarm detection module circuit diagram	54
4.6	How detection being made on burglar alarm module	54

4.7	How baby cry module being tested	56
4.8	Testing temperature sensor	57
4.9	Testing on the door bell module	58
4.10	Testing the burglar alarm sensor module	59
4.11	Testing on rain detector module	60
4.12	Integration of sensors with the main controller unit	61
4.13	Wrist alert unit located near the main controller unit	63
4.14	LCD on wrist alert display House On Fire when temperature sensor activated	64
4.15	LCD on wrist alert display Baby crying when baby cry sensor activated	65
4.16	Double storey house to test the RF performance	65
4.17	1st floor layout of the tested double storey house	66
4.18	2nd floor layout of the tested double storey house	67

**LIST OF ABBREVIATIONS**

ACS	-	Adjacent channel selectivity
ALD	-	Assistive Listening Device
BTE	-	Behind-the-Ear
dB	-	Decibel
GSM I	-	Global System for Mobile
ITC	-	The In-the-Canal
LED	-	Light Emitting Diode
LCD	-	Liquid Crystal Display
NTC	-	Negative Temperature coefficient
PPP	-	PICmicro Parallel Programmer
PIC	-	Peripheral Interface Controller
RF	-	Radio Frequency
TE	-	Communication In-the-Ear

**LIST OF APPENDICES**

<b>APPENDIX</b>	<b>TITLE</b>	<b>PAGE</b>
A	Bill of Material ( BOM)	79
B	PIC 16F84A datasheet	84
C	Main controller and wrist alert units drawing	88
D	C Program for main controller and wrist alert units	91
E	Interview session with hearing impaired people	111



## **CHAPTER 1**

### **INTRODUCTION**

#### **1.1 Overview**

The number of hearing problem among Malaysia citizen is very high. Statistics 2005 shows that there are 26294 hearing impaired people in Malaysia (Department of social Welfare Malaysia, 2007). There are hearing aid hearing aids and ALD devices in the market to help these people on their daily activities but mostly are not locally made and expensive. Moreover not all suitable or fits the individual needs and the maintenance cost or installation could be expensive due to no local expertise.

## 1.2 Objectives

- i. To design a prototype of home notification system for hearing impaired people that can fulfill five basic notification system ; notify the house on fire, baby's crying, burglar alarm notification system, to notify someone ringing the door bell and weather starts raining.
- ii. To develop fire alarm system when temperature sensor detect heat.
- iii. To design wireless communication between the controller and the wrist alert system using Radio Frequency (RF).
- iv. Select the suitable wireless medium for the application.
- v. To develop a mobile alerter system that fit to the size of human wrist (wrist alerter) and select the suitable output / alert system for hearing impaired users which LCD display and vibrator are the outputs.
- vi. To integrate all of the components needed, choose the right controller, compile and do the testing at real time.
- vii. To build up the system with the all basic home notification signals at one reasonable cost. The system should be not be more than RM500.

### **1.3 Scope of Work**

The control or working area of the project is being narrowed to an in-door or home environment. Alert signals are connected to a centralized controller box, will be processed and transmitted via a wireless communication link to the wireless wristband device while the communication between signals from sensors and detectors to the controller box are wired. The type of notification signals would be four basic signals such as doorbells, incoming telephone signal, baby monitor, rain detector signal and an extra temperature alarm signal for their safety purpose. Target of users would be the hearing any hearing impaired categories, single, married or old citizen.

In order to achieve the objectives of the projects, need study some several area that related to the project such as the wireless technology, smart house characteristics , microcontrollers, sensor technology and having an interview with the hearing impaired people in order to get the information and to understand their difficulties in the house.

### **1.4 Project Background**

Statistics 2005 shows that there are 26294 hearing impaired people in Malaysia (Department of social Welfare Malaysia, 2007) Many surveys show that one out of ten people suffers from hearing loss and would benefit from using hearing aids. Nobody knows the exact number of hearing-impaired people, but most estimates set the figure around 500 million. (Hear-it.org, 2007). Unfortunately, most of the home appliance products today are meant for normal people and it is not user friendly for the

handicapped people generally. It is not denied there are hearing aid and Assistive Listening Device (ALD) in the market but there is no best for every body due to large variety of hearing losses and for several basic notification system, the hearing impaired people need to pay an amount of money which is not everybody can afford them. Other than that, the notification system product for hearing impaired on the market are not locally made and have also several disadvantages such as using license frequency where need to pay to the authority, no local expertise if there are problem in installation or troubleshooting. Despite to the growth of wireless communication, unlicensed RF is still being used due to one of the cheapest wireless system, where there's no third party involved such as GSM and GPRS system and suitable for daily notification system.

### **1.5 Expected result**

- i. The main controller unit and wrist alert unit able to communicate wireless.
- ii. All the inputs sensors or input signals should be functioning and able to communicate with the main controller unit.
- iii. The LCD could display the output according to the situations.
- iv. The main controller able to differentiate and send the output data according to the priority of the signals.
- v. The wrist alert unit should not very big and can be worn by the users.
- vi. The total cost should be at reasonable price.