

Characterization of the koch fractal embedded hexagonal loop frequency selective surface structure for X-band application

Nur Biha Mohamed Nafis¹, Mohamad Kamal A. Rahim², Osman Ayop³, Huda A Majid⁴,
Sunti Tuntrakool⁵

^{1,2,3}Advance RF and Microwave Research Group (ARFMRG), School of Electrical Engineering, Faculty of Engineering, Universiti Teknologi Malaysia, Malaysia

¹Department of Physics, Faculty of Science, Universiti Putra Malaysia, Malaysia

⁴Faculty of Engineering Technology (FTK), Department of Electrical Engineering Technology, Universiti Tun Hussein Onn Malaysia, Malaysia

⁵Faculty of Industrial Education and Technology, King Mongkut's Institute of Technology Ladkrabang (KMITL), Thailand

Article Info

Article history:

Received Jan 18, 2020

Revised Apr 20, 2020

Accepted May 4, 2020

Keywords:

Fractal

Frequency selective surface

Hexagonal loop

Koch

X-band

ABSTRACT

This paper presented the bandstop Koch fractal embedded hexagonal loop frequency selective surface (FSS) for the X-band application. The simulated transmission coefficient response (S_{21}) had been obtained by using CST software. The surface current distribution and the electric field density are illustrated to explain in detail the S_{21} of the fractal based FSS structure. The proposed structure is highly insensitive towards angular stability and also polarization independent up to 70° . The parametric analysis on the effect of the periodicity, width, and height of the fractal FSS structure on the S_{21} has been illustrated and discussed thoroughly.

Copyright © 2020 Institute of Advanced Engineering and Science.
All rights reserved.

Corresponding Author:

Mohamad Kamal A. Rahim,
Advance RF and Microwave Research Group (ARFMRG),
School of Electrical Engineering,
Faculty of Engineering,
Universiti Teknologi Malaysia,
UTM Johor Bahru (UTMJB) Johor 81310, Malaysia.
Email: mdkamal@utm.my

1. INTRODUCTION

The frequency selective surface (FSS) which also known as a spatial filter, is made up of 1-D or 2-D infinite periodic array of similar elements that allows the transmission and reflection of the plane wave that incident onto the structure [1]. An American physicist, David Rittenhouse, had discovered the potential of FSS to be used as spatial filter when he found out that the light spectrum's colors being filtered through a silk scarf while observing a lamp, and became the pioneer for the study of the FSS structure. The filter response of a FSS is highly dependent on the two different array geometries, which are the patches and the slots. The patch array and the slot array represent the low pass filter characteristic and high pass filter characteristic, respectively, which can be explained by the Babinet's principle. The combination of both arrays can yield the bandpass and bandstop filter characteristics. For the traditional FSS, a longer electrical length is required especially for the low frequency response. Furthermore, some applications require a smaller-sized FSS screen to achieve better filter performance. The parameters such as multiband and wide BW behavior, angular stability, and polarization independent properties are unachievable by utilizing the traditional FSS geometry, which can deteriorate the filter's performance. To address these limitations, the utilization of the fractal structure is suggested to miniaturize the dimension of the FSS.

In 1991, the idea of utilizing fractal geometry such as Minkowski loop and the Hilbert curve had been introduced by Parker and El sheikh [2], to miniaturize the FSS structure. Few factors had led to the utilization of fractal geometry onto the FSS structure. The first factor is that a large number of traditional FSS unit cell required for obtaining the specified frequency response based on the mutual interactions of the unit cells [3]. The small size of the FSS screen is required for some applications to achieve high angular stability response. Furthermore, the traditional FSS geometry unable to provide the best filter's performance in terms of multiband and broad bandwidth (BW) behaviors, angular stability and polarization independence [4]. Thus, fractal geometry is introduced to overcome these limitations. The uniqueness of the self-similarity of the fractal frequency selective surface structure had been reported widely in numerous studies for different applications [3, 5-11], which includes multiband and wide BW behavior, angular independent operations and low grating lobes appearance in a compact design.

Previously, the utilization of hexagonal geometry for FSS structure is proven to have higher angular stability than the traditional square geometry of FSS [12, 13]. The hexagonal geometry also able to employ the multiband and wide BW behavior that have high insensitivity towards angular stability and polarization independence. The hexagonal slot geometry had been applied together with Koch fractal structure as in [12] to achieve multiband and wide BW passband filter. For this paper, the utilization of Koch fractal to the hexagonal loop FSS structure is analyzed and discussed in detail in terms of frequency response behavior, angular stability and polarization independence. When the Koch fractal structure embedded to the hexagonal loop FSS structure, with the increased of the iteration level to 2nd level, the transmission coefficient (S_{21}) exceeding -10 dB over the range of 2.23GHz (from 8.24 GHz to 10.47 GHz), which is resonated at frequency of 9.5 GHz and thus applicable for X-band application. The proposed fractal FSS structure has higher stability toward angular stability at higher iteration level. However, for the TE mode polarization, the BW increased, while for the TM mode polarization, the BW decreased continuously as the oblique angles increased. The BW enhancement for the entire X band (8 GHz to 12 GHz) can be further study in the future. The parametric study which includes the periodicity, width and also the height of the proposed Koch fractal hexagonal loop FSS structure had been simulated by the CST software and discussed in detail in the results and discussions section.

2. DESIGN OF FRACTAL-BASED FREQUENCY SELECTIVE SURFACE

For the hexagonal loop structure, (1) shows that the resonant frequency (f_r) can be deduced when the electrical length of the geometry structure is half wavelength. As the FSS structure does not have the ground plane, the f_r is highly dependent on the electromagnetic properties FSS structural element.

$$f_r = \frac{c}{2 \times l \times \sqrt{\epsilon_{eff}}} \quad (1)$$

$$\epsilon_{eff} = \frac{\epsilon_r + 1}{2} \quad (2)$$

where c is the speed of light, ϵ_{eff} is the effective permittivity and ϵ_r is the permittivity of the dielectric material.

For the Koch fractal structure, the Iterated Function System (IFS), which was invented by John Hutchinson, was applied to the fractal structure by using the affine transformations, as reported in several previous studies [14-17]. Based on (3), a two-dimensional affine transformation, w , was introduced on the Euclidean plane, in which the parameters are represented by six variables (i.e., a, b, c, d, e , and f).

$$w \begin{pmatrix} x \\ y \end{pmatrix} = \begin{pmatrix} a & b \\ c & d \end{pmatrix} \begin{pmatrix} x \\ y \end{pmatrix} + \begin{pmatrix} e \\ f \end{pmatrix} \quad (3)$$

where the matrix of a, b, c and d , is defined as a linear transformation that includes a combination of rotation, scaling, and a shear, and then translated by the matrix of e and f .

For the acquired low frequency, a large FSS dimension is required to accommodate the longer electrical lengths, and this could result in the appearance of grating lobes [1, 18]. The grating lobe phenomenon arises due to large spacing between the unit cell elements (D) as well as the angle of the incident wave depicted in (4).

$$D < \frac{\lambda_o}{1 + \sin \theta} \quad (4)$$

where λ_o is the resonant wavelength of the FSS and θ is the angle of the incident wave.

Based on the (4), the periodicity of the unit cell should be less than the λ_o at initial incident angle. With a higher value of incident angle, the unit cell periodicity should be half the free space wavelength to prevent the occurrence of the grating lobe phenomena—a limitation that can be prevented by implementing a fractal structure to miniaturize the FSS. For example, extensive studies over the past decade have integrated patch or slot elements with the fractal structures such as the Koch fractal structure [3, 19], the Minkowski [20] and the Minkowski island [21], the Interdigital fractal structure [22], the Sierpinski fractal structure [23], the Swastika fractal structure [24] etc., to reduce the size of the FSS element.

All the hexagonal loop and the proposed Koch fractal hexagonal loop FSS structures had been simulated by using the CST software. The FR4 substrate with ϵ_r of 4.3 and the 1.6-mm-thick lossy substrate, with 0.035-mm-thick copper layer with a conductivity of $5.8 \times 10^7 \text{ S/m}$, had been used as the dielectric substrate. Figure 1 shows the hexagonal loop and the proposed Koch fractal hexagonal loop FSS structures with optimized parameters such as the unit cell periodicity ($p = 7.22 \text{ mm}$), the width of the hexagonal loop ($w = 0.20 \text{ mm}$) and the side length of the hexagonal loop ($l = 3.33 \text{ mm}$), which resonated at 11.03 GHz. The proposed Koch fractal hexagonal loop FSS structure which employed the first and the second iteration levels of the Koch fractal structure are shown in Figure 1(b) and 1(c). Figure 1d shows the simulation of a unit cell of the proposed FSS structure with unit cell boundary condition to simulate the frequency response of the proposed FSS.




Figure 1. The hexagonal loops FSS structures. (a) hexagonal loop FSS, (b) 1st iteration level of Koch fractal hexagonal loop FSS, (c) 2nd iteration level of Koch fractal hexagonal loop FSS, (d) A unit cell of the proposed FSS with unit cell boundary conditions to simulate the frequency response of the proposed FSS

The self-similarity feature of the Koch fractal structure based on (5) has allows the miniaturization of the FSS structure for obtaining the specified X-band frequency.

$$D = \frac{\log N}{\log\left(\frac{1}{sf}\right)} \quad (5)$$

where sf = scaling fraction

N = copies of the original geometry to be made

D = self-similarity dimension

3. RESULTS AND DISCUSSION

For bandstop fractal based FSS structure, the parameters such as f_r , S_{21} , BW, angular stability and polarization independence were studied for determining the best performance of the bandstop fractal-based FSS structure for X-band application. Figure 2 shows the simulated S_{21} results of the hexagonal loop and the proposed Koch fractal hexagonal loop FSS structures. Generally, the increasing of the iteration level would shift the f_r to the low frequency region, which is agreeable with the simulated S_{21} results. For the hexagonal loop FSS, the initial values of f_r and BW are 11.03 GHz and 2.67 GHz, respectively. When the Koch fractal structure embedded to the hexagonal loop FSS structure, with the increased of the iteration level to 2nd level, the f_r and BW had decreased to 9.5 GHz and 2.23GHz (from 8.24 GHz to 10.47 GHz), respectively.






Figure 2. The simulated S_{21} for the hexagonal loop fractal based FSS structures. (a) hexagonal loop FSS, (b) 1st iteration level and (c) 2nd iteration level of Koch fractal hexagonal loop FSS

Previously, it is known that the ability of the hexagonal geometry in providing better performance of FSS structure in terms of angular stability and polarization [12, 13]. Figure 3 depicted the simulated S_{21} of the basic and the proposed Koch fractal hexagonal loop FSS structure for TE and TM polarized wave incidence at the variation of oblique angles ($0^\circ, 10^\circ, 20^\circ, 30^\circ, 40^\circ, 50^\circ, 60^\circ, 70^\circ$). By comparing the first and the second iteration level of Koch fractal, the shifting of the f_r as the increasing of oblique angles is less pronounced at higher iteration level of the fractal structure. However, for the TE mode polarization, the BW increased, while for the TM mode polarization, the BW decreased continuously as the oblique angles increased.



(a) TE mode



(b) TM mode polarization for 1st iteration level of Koch fractal hexagonal loop FSS




Figure 3. The simulated S_{21} at variation of oblique angles ($0^\circ, 10^\circ, 20^\circ, 30^\circ, 40^\circ, 50^\circ, 60^\circ, 70^\circ$)

Figure 4 depicted the surface current distribution and the electric energy density (the distribution of the electric field) for the hexagonal loop and also the proposed Koch fractal hexagonal loop FSS structure, for better understanding of the fractal FSS's physical mechanism. It can be observed that in Figures 4(a), 4(b) and 4(c), the strongest surface current density exists on the left and the right sides of the hexagonal loop structures. As the iteration level increased, the stronger surface current density appeared at the Koch fractal geometry of the hexagonal loop FSS structure. Figure 4(d), 4(e) and 4(f) show the E-field distribution of the hexagonal loop and also the proposed Koch fractal hexagonal loop FSS structures. It can be seen that the edge center of up and down sides of the hexagonal loop and the proposed Koch fractal hexagonal loop FSS structure had the strongest distribution of E-field. Based on this information, it is agreeable that the length of the current path is increased proportionally with the iteration level of the Koch fractal as can be seen in Figure 4, which lead to the reduction of f_r as in (1) and allows the specify f_r to be obtained.




Figure 4. The surface current distribution of (a) hexagonal loop FSS, (b) 1st iteration level of Koch fractal hexagonal loop FSS, and (c) 2nd iteration level of Koch fractal hexagonal loop FSS; The E-field distribution of (d) hexagonal loop FSS, (e) 1st iteration level of Koch fractal hexagonal loop FSS, and (f) 2nd iteration level of Koch fractal hexagonal loop FSS

3.1. Parametric analysis

The parametric analysis on the physical mechanism of the proposed Koch fractal hexagonal loop FSS structure had been done for investigating the effect of the periodicity (p), width (w) and height of the Koch fractal on the S_{21} response. Figure 5 shows the simulated S_{21} response for various ‘ p ’ value. It can be observed that for both of the iteration level of Koch fractal hexagonal loop FSS structure, the f_r would be shifted to the high frequency region and at the same time, would decrease the value of BW and S_{21} as the periodicity increased. The values of BW and S_{21} with the periodicity of 7.0 mm are 2.33 GHz (8.33 GHz ~ 10.66 GHz) and -30.35 dB respectively, for the first iteration level of the Koch fractal. As the periodicity increased up to 8.0 mm, the decreased values of BW and S_{21} are 1.85 GHz (9.03 GHz ~ 10.88 GHz) and -27.71 dB, respectively. For the second iteration, the values of BW and S_{21} with the periodicity of 7.0 mm are 2.36 GHz (8.0834 GHz ~ 10.438 GHz) and -30.20 dB respectively. As the periodicity increased up to 8.0 mm, it affected the values of BW and S_{21} which are 1.78 GHz (8.84 GHz ~ 10.62 GHz) and -27.54 dB, respectively. This is because the metal area in unit cell decrease, so the reflected power is lower, hence attenuation level in transmission is lower as well [25].




Figure 5. The simulated S_{21} results of the variation of the periodicity of hexagonal loops fractal based FSS structures. (a) 1st iteration level and (b) 2nd iteration level of Koch fractal hexagonal loop FSS

The simulated S_{21} response for variation of ‘ w ’ is depicted in Figure 6. For both of the iteration level, the initial width of the proposed Koch fractal hexagonal loop FSS structure provides the BW of 2.14 GHz (8.62 GHz ~ 10.76 GHz) for the first iteration and 2.23 GHz (8.24 GHz ~ 10.47 GHz) for the second iteration level of fractal FSS structure. It can be seen that the increase of ‘ w ’ up to 0.5 mm had resulted in an increased value of BW and f_r , which is more significant for the second iteration level of the Koch fractal hexagonal loop FSS structure. However, the increased of ‘ w ’ would disturb the compactness of the fractal FSS structure.




Figure 6. The simulated S_{21} results of the variation of ‘ w ’ of hexagonal loops fractal based FSS structures. (a) 1st iteration level and (b) 2nd iteration level of Koch fractal hexagonal loop FSS

Figure 7 shows the effect of the height of the Koch fractal geometry on the S_{21} response. The height of the Koch fractal is highly dependent on the indentation angle of the Koch fractal geometry structure, as the changes of the indentation angle are proportional to the changes of the height of the Koch fractal. The height of the Koch fractal is varied from 0.34 mm up to 0.98 mm for variation of indentation angle (20°, 30°, 40°, 50°, 60°, 70°, 80°). Based on Figure 7, at both iteration level, the value of f_r had shifted to the left and the value of BW had decreased further. As the height increased, the electrical length of the Koch fractal is increased which lead to the decreased of the f_r , that is agreeable with the (1).




Figure 7. The simulated S_{21} results of the variation of the height of the Koch fractal hexagonal loops FSS structures. (a) 1st iteration level and (b) 2nd iteration level of Koch fractal hexagonal loop FSS

4. CONCLUSION

In this paper, the design, the analysis of simulated S_{21} , and also the parametric analysis (periodicity, width, height) for the proposed Koch fractal hexagonal loop FSS structure is presented. The employment of Koch fractal to the hexagonal loop FSS structure is analyzed and discussed in detail in terms of frequency response behavior, angular stability and polarization independence. The fractal FSS structure is composed of Koch fractal hexagonal loop FSS structure. The proposed fractal FSS design provides -10 dB BW of 2.23 GHz (from 8.24 GHz to 10.47 GHz) at f_r of 9.5 GHz, as well as higher angular stability and polarization independence, at second iteration level of Koch fractal geometry. However, for the TE mode polarization, the BW increased, while for the TM mode polarization, the BW decreased continuously as the oblique angles increased. For future work, the BW enhancement for the entire X band (8 GHz to 12 GHz) for the Koch fractal hexagonal loop FSS structure can be further study.

ACKNOWLEDGEMENTS

The authors would like to express utmost gratitude to the Advance RF and Microwave Research Group (ARFMRG) in Universiti Teknologi Malaysia (UTM) for supporting this work. This work was supported by Ministry of Education (MOE), Research Management Centre (RMC), School of Electrical Engineering, Faculty of Engineering Universiti Teknologi Malaysia (UTMJB) Johor Bahru under vot number 04G65 and 06G15.

REFERENCES

- [1] B. A. Munk, "Frequency Selective Surfaces: Theory and Design". New York: *John Wiley & Sons*, 2000.
- [2] E. A. Parker and A. N. A. El sheikh, "Convulated array elements and reduced size unit cells for frequency-selective surfaces," *IEE Proc. H Microwaves, Antennas Propag.*, vol. 138, no. 1, p. 19, 1991, doi: 10.1049/ip-h-2.1991.0004.
- [3] A. L. P. S. Campos, E. E. C. de Oliveira, and P. H. F. Silva, "Miniaturization of frequency selective surfaces using fractal Koch curves," *Microw. Opt. Technol. Lett.*, vol. 51, no. 8, pp. 1983-1986, Aug. 2009, doi: 10.1002/mop.24503.

- [4] K. Sarabandi and N. Behdad, "A Frequency Selective Surface With Miniaturized Elements," *IEEE Trans. Antennas Propag.*, vol. 55, no. 5, pp. 1239-1245, May 2007, doi: 10.1109/TAP.2007.895567.
- [5] T. Hussain, Q. Cao, J. K. Kayani, and I. Majid, "Miniaturization of Frequency Selective Surfaces Using 2.5-D Knitted Structures: Design and Synthesis," *IEEE Trans. Antennas Propag.*, vol. 65, no. 5, pp. 2405-2412, May 2017, doi: 10.1109/TAP.2017.2673809.
- [6] S. Suganthi, K. S. Tharini, P. S. Sarankumar, S. Raghavan, and D. Kumar, "Design and simulation of planar Minkowski fractal antennas," in *2011 2nd International Conference on Wireless Communication, Vehicular Technology, Information Theory and Aerospace & Electronic Systems Technology (Wireless VITAE)*, pp. 1-5, 2011, doi: 10.1109/WIRELESSVITAE.2011.5940935.
- [7] J. I. A. Trindade, P. H. da F. Silva, A. L. P. S. Campos, and A. G. D'Assuncao, "Analysis of Stop-Band Frequency Selective Surfaces With Dürer's Pentagon Pre-Fractals Patch Elements," *IEEE Trans. Magn.*, vol. 47, no. 5, pp. 1518-1521, May 2011, doi: 10.1109/TMAG.2010.2091112.
- [8] P. H. da F. Silva, C. de L. Nóbrega, M. R. da Silva, and A. G. D'Assunção, "Optimal design of frequency selective surfaces with fractal motifs," *IET Microwaves, Antennas Propag.*, vol. 8, no. 9, pp. 627-631, Jun. 2014, doi: 10.1049/iet-map.2013.0462.
- [9] J. P. Gianvittorio and Y. Rahmat-Samii, "Fractal geometry in antenna system design: miniaturized-multiband element, phased array and frequency selective surface design," in *2002 3rd International Conference on Microwave and Millimeter Wave Technology, 2002. Proceedings. ICMMT 2002.*, pp. 508-511, 2002, doi: 10.1109/ICMMT.2002.1187748.
- [10] F. Bayatpur and K. Sarabandi, "Single-Layer High-Order Miniaturized-Element Frequency-Selective Surfaces," *IEEE Trans. Microw. Theory Tech.*, vol. 56, no. 4, pp. 774-781, Apr. 2008, doi: 10.1109/TMTT.2008.919654.
- [11] F. C. Seman and N. K. Khalid, "Investigations on fractal square loop FSS at oblique incidence for GSM applications," in *2014 Electrical Power, Electronics, Communications, Control and Informatics Seminar (EECCIS)*, pp. 62-66, 2014, doi: 10.1109/EECCIS.2014.7003720.
- [12] H. Ullah, F. A. Tahir, and M. El-Hadidy, "FSS based Hexo-Fractal Dual Passband Filter for 28 and 38 GHz 5G Millimeter-Wave Communications," in *2018 IEEE International Symposium on Antennas and Propagation & USNC/URSI National Radio Science Meeting*, pp. 2365-2366, 2018, doi: 10.1109/APUSNCURSINRSM.2018.8608229.
- [13] C. Guan, X. Ding, Y. Wu, and Q. Wu, "A Dual-Band Frequency Selective Surface with Wide Bandwidths," in *2018 International Conference on Microwave and Millimeter Wave Technology (ICMMT)*, pp. 1-3, 2018, doi: 10.1109/ICMMT.2018.8563846.
- [14] H. O. Peitgen, H. Jurgens, and D. Saupe, "Chaos and Fractals: New Frontiers of Science". New York: Springer-Verlag, 1992.
- [15] M. F. Barnsley, *Fractals Everywhere*, Second Edi. New York: Academic Press Professional, 1993.
- [16] D. H. Werner and S. Ganguly, "An overview of fractal antenna engineering research," *IEEE Antennas Propag. Mag.*, vol. 45, no. 1, pp. 38-57, Feb. 2003, doi: 10.1109/MAP.2003.1189650.
- [17] D. H. Werner and P. L. Werner, "Genetically engineered dual-band fractal antennas," in *IEEE Antennas and Propagation Society International Symposium. 2001 Digest. Held in conjunction with: USNC/URSI National Radio Science Meeting (Cat. No.01CH37229)*, vol. 3, no. 19, pp. 628-631, 2001, doi: 10.1109/APS.2001.960175.
- [18] T. K. Wu, "Frequency Selective Surface and Grid Array". New York: Wiley, 1995.
- [19] R. H. C. Manicoba, A. L. P. S. Campos, T. de Lima Silva, and A. G. D'Assuncao, "Experimental investigation of FSS cascading with fractal elements," in *2011 SBMO/IEEE MTT-S International Microwave and Optoelectronics Conference (IMOC 2011)*, pp. 689-693, 2011, doi: 10.1109/IMOC.2011.6169231.
- [20] D. B. Brito, L. M. Araujo, A. G. D'Assuncao, and R. H. C. Manicoba, "A Minkowski fractal Frequency Selective Surface with high angular stability," in *2013 SBMO/IEEE MTT-S International Microwave & Optoelectronics Conference (IMOC)*, pp. 1-4, 2013, doi: 10.1109/IMOC.2013.6646577.
- [21] A. L. P. S. Campos, E. E. C. de Oliveira, and P. H. F. Silva, "Design of miniaturized frequency selective surfaces using minkowski island fractal," *J. Microwaves, Optoelectron. Electromagn. Appl.*, vol. 9, no. 1, pp. 43-49, 2010.
- [22] T. Zhong, H. Zhang, R. Wu, and X. Min, "Novel Dual-Band Miniaturized Frequency Selective Surface based on Fractal Structures," *Frequenz*, vol. 71, no. 1-2, pp. 57-63, Jan. 2017, doi: 10.1515/freq-2016-0010.
- [23] C. de Lucena Nóbrega, M. Ribeiro da Silva, P. H. da Fonseca Silva, and A. G. D'Assunção, "A compact frequency selective surface with angular stability based on the Sierpinski fractal geometry," *J. Electromagn. Waves Appl.*, vol. 27, no. 18, pp. 2308-2316, Dec. 2013, doi: 10.1080/09205071.2013.842939.
- [24] M. Fallah, A. H. Nazeri, and M. R. Azadkhan, "A Novel Fractal Multi-band Frequency Selective Surface," *J. Microwaves, Optoelectron. Electromagn. Appl.*, vol. 18, no. 2, pp. 276-285, Jun. 2019, doi: 10.1590/2179-10742019v18i21559.
- [25] S. R. Dantas, E. B. Cadineli, A. L. P. S. Campos, and A. Gomes Neto, "Proposal of a fractal geometry with double similarity ratio for application in frequency selective surfaces with insensitive resonance frequency as a function of cell periodicity," *Microw. Opt. Technol. Lett.*, vol. 60, no. 3, pp. 654-659, Mar. 2018, doi: 10.1002/mop.31029.

BIOGRAPHIES OF AUTHORS



Nur Biha Mohamed Nafis received the bachelor's degree in instrumentation science and the master's degree in applied physics from Universiti Putra Malaysia (UPM). She is currently pursuing her Ph.D. degree in Electrical engineering at Universiti Teknologi Malaysia (UTM).



Mohamad Kamal A Rahim has received the B Eng. degree in Electrical and Electronic Engineering from University of Strathclyde, UK, in 1987. He obtained his M.Eng Science from University of New South Wales Australia in 1992 and PhD degrees in Electrical Engineering from the University of Birmingham UK in 2003. From 1987 to 1989, he worked as a Management Trainee at Sime Tyres Mergong Alor Star Kedah and Production Supervisor at Sime Shoes in Kulim Kedah. In 1989, he joined the Department of Communication Engineering, Faculty of Electrical Engineering Universiti Teknologi Malaysia Kuala Lumpur as an Assistant Lecturer. After he received his Master, he was appointed as a Lecturer at the Faculty of Electrical Engineering. In 2005 he was appointed as a senior lecturer, and in 2007 he was appointed as Assoc Professor at the faculty. Now he is the Professor in RF and Antenna at School of Electrical Engineering, Faculty of Engineering, Universiti Teknologi Malaysia. His research interest includes the areas of design of Dielectric resonator antennas, microstrip antennas, small antennas, microwave sensors, RFID antennas for readers and tags, Multi-function antennas, microwave circuits, EBG, artificial magnetic conductors, metamaterials, phased array antennas, computer-aided design for antennas and design of millimetre frequency antennas. In the year 2018, he was awarded as Distinguished Researcher during CITRA KARISMA 2018, and at the same year, he was awarded as Top Research Scientist under Academy Science Malaysia.



Osman Ayop received the Ph.D. degree in Electrical Engineering (2016), M.S. degree in Electrical Engineering (2010) and B.S. degree in Electrical Engineering - Telecommunication (2007) from Universiti Teknologi Malaysia. Previously, he was a Tutor in Department of Communication Engineering, Faculty of Electrical Engineering (Now is known as School of Electrical Engineering, Faculty of Electrical), Universiti Teknologi Malaysia from 28 April 2008 until 4 April 2016. He had done his attachment in Uppsala University of Sweden (2013) under the supervision of Prof. Dr Vernon Cooray in Amstrong Lab during the winter semester. He has been appointed as a Senior Lecturer in Faculty of Electrical Engineering UTM from 5 April 2016 until today. His research interests are in the field of antennas, propagation, and also metamaterials. He is also an active researcher in Advanced RF and Antenna Research Group (ARFMRG) and has been participated in a lot of courses, seminars, exhibition etc. He has been published numerous journals, proceedings, research books, and book chapters and also won several university and national awards related to his research works. He has been appointed as a reviewer for several national/international journals and conferences.



Huda A Majid received the B.Eng. degree in electrical engineering (telecommunication) and the M.Eng. and Ph.D. degrees in electrical engineering from Universiti Teknologi Malaysia in 2007, 2010, and 2013, respectively. His research interests include design of microstrip antennas, small antennas, reconfigurable antennas, metamaterials structure, metamaterial antennas, and millimeter-wave antennas. He has published over 50 articles in journals and conference papers.



Sunti Tuntrakool received the B.S. degree in industrial education in telecommunication engineering major from King Mongkut's Institute of Technology Ladkrabang, Ladkrabang, Bangkok, Thailand, in 1993 and the M.S. degree in electrical engineering from Vanderbilt University, Nashville TN, in 2004. His research interests include digital signal processing, biomedical signal processing, mouse renal sympathetic nerve activity, and autonomic control of the cardiovascular system.