DESIGN AND FABRICATION OF A POLYMER BASED DIRECTIONAL COUPLER THERMOOPTIC SWITCH

ABU SAHMAH BIN MOHD SUPA'AT

A thesis submitted in fulfilment of the requirements for the award of the degree of Doctor of Philosophy

> Faculty of Electrical Engineering Universiti Teknologi Malaysia

> > AUGUST 2004

DEDICATIONS

Especially dedicated to my beloved parents, my wife, my children, my siblings and all my friends for their support, confidence and understanding with love and respect.

ACKNOWLEDGEMENTS

All praise to ALLAH S.W.T for the guidance, strength and perseverance bestowed upon me to finish this work. It is through His grace that the present thesis has come into existence.

This thesis is the result of the past three years research in which I had worked and learnt many things. During such a period of time, there are many people from peer group who had their positive influence on the work of a graduating student.

I would first like to express my most sincere thanks to my supervisor Professor Dr. Abu Bakar bin Mohammad for introducing me into the field of optical communications and thereafter giving me the freedom to learn and grow and for opening doors of opportunity to study in this research work. I have had the extreme good fortune to share in his knowledge, insight and vision both within and beyond the bounds of this work. I would also like to thank my co-supervisor Associate Professor Dr. Norazan bin Mohd Kassim for his advice, knowledge and help whenever needed as I prepared this work.

I am indebted to my friends and colleagues, Mahmud, Razali, Fakheruddin, Cheah Wei, Rosli, Haniff and Khaled who have been there with me throughout the past two and three years by providing the motivation for this research through pioneering efforts in the area of optical switching and have offered critical insight and direction in this work from its inception through its completion.

I would also wish to express my gratitude to Professor Dr. Rene de Ridder and Professor Dr. Mart Diemeer of MESA Research Institute for their useful discussion and advice during my internship in Lightwave Device Group, University of Twente, the Netherlands. I would also like to acknowledge the help of many people at Zenphotonics Korea, Dr. Wol Yon Hwang, Dr. Min Cheol Oh and in particular Dr. Dang Sung Kang, the head of fabrication laboratory of Zenphotonics for useful discussion, enthusiasm, helpfulness and friendship which have brought much excitement into this work and provided me with a first hand experience of the wonderful Korean hospitality.

The financial support of Universiti Teknologi Malaysia (UTM) and the Malaysian Ministry of Science Technology and Environment (MOSTE) for funding of this research work is gratefully acknowledged.

Finally and yet most importantly, my sincere thanks to my wife Dr. Zaleha binti Nassir and my children, Ahmad Syahir, Ahmad Fuad, Nurul Atiqah, Ahmad Fadzli and Ahmad Murtadha for their immense patient, great understanding and convincing attention during the hectic period of this study.

PUBLICATIONS, AWARDS AND PATENT

The following papers, awards and patent, based on the work described in this thesis has been published:

- Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Digital electrooptic modulators synthesized from directional couplers. Proceedings 5th. IEEE Malaysia International Conference on Comm. and 2nd. East Asean Conference Lightwave System Lasers Optoelectronics (MICC 2001 & LISLO 2001). 376-379. Oct. 2001.
- Mohd Supa'at, A. S., Mohammad, A. B., Mohd Kassim, N. and Omar, R. Analysis of mode fields in optical waveguides. *International Conference on Computers, Comms., Control and Power Engineering. IEEE TENCON '02.* Oct. 2002.
- Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Design of buried type polymer based waveguide optical directional coupler. *IEEE International Conference on Semiconductor Electronics*. *ICSE* 2002 Proceeding. 397-401. December 2002.
- Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Fabrication of Thermooptic Switch Using Polymers. *IEEE National Symposium on Microelectronics. NSM 2003.* 8-11. September 2003.
- Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Design of parallel waveguide using electrooptic effect in controlling the coupling of light. *Journal Institution of Engineers, Malaysia. Special Issue ELECTRICAL*. 63(1). 33-36. March 2002.

 Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Modelling techniques for rectangular dielectric waveguides-ribs waveguides. *Jurnal Teknologi*. 36(D). 29-143. Jun 2002.

Awards:

- Silver Medal:- 2X2 Thermooptic Photonic Switch. Expo Science and Technology (Expo S&T) 2003 at Pusat Dagangan Dunia Putra (PWTC), Kuala Lumpur. 7 – 9 August. 2003.
- Special Jury's Award:- 2X2 Thermooptic Polymer based Optical Switch. Industrial Art and Technology Exhibition (INATEX). Universiti Teknologi Malaysia. Johor Bahru. 17-19 September. 2003.
- Gold Medal:-Thermooptic Photonic Switch. 32nd. International Exhibition of Invention, New Techniques and Products of Geneva. 30 March – 4 April. 2004.

Patent:

1. Patent Pending:- Thermooptic Photonic Switch.

Submitted and awaiting review:

- A. S. M. Supa'at, A. B. Mohammad and N. M. Kassim. Thermal analysis: Induced temperature profiles of polymer waveguide. *Submitted for Journal Institute of Engineers Singapore. IES.*
- Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Polymer based directional coupler thermooptic optical switch. Submitted for Jurnal Teknologi.

- 3. A. S. M. Supa'at, A. B. Mohammad and N. M. Kassim. Low Cost Waveguide based Switch using all polymers with Low Power Consumption. *Submitted for Journal on Wireless and Optical Communications*.
- 4. Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Low power consumption thermooptic switch using polymers. Submitted for Journal of Industrial Technology, SIRIM.
- Abu Sahmah Mohd Supa'at, Abu Bakar Mohammad and Norazan Mohd Kassim. Design of polymer based directional coupler thermooptic optical switch. *Submitted for ICECE*, 2004.
- Abu Bakar Mohammad, Abu Sahmah Mohd Supa'at and Norazan Mohd Kassim. Development of 2x2 asymmetrical thermooptic switch. *Submitted for ICECE*, 2004.

ABSTRACT

This thesis is concerned with the development of optical switches, which are essential components for wavelength division multiplexed optical networks. А waveguide type 2X2 thermooptic polymer optical switch based on generalized directional coupler interferometer operating at 1550 nm for singlemode operation has been designed and fabricated. Three research topics in the development of optical switches were unified through the use of polymer materials in photonic devices. The topics are; a unique formulation of two and three dimensional model of planar dielectric waveguide using MATLAB for accurate simulation of straight waveguides and waveguides bend. Secondly, a thermal analysis used for the calculation of the temperature profile and the resulting phase shift due to thin film heater electrodes in polymers using MATLAB for switching functions and finally, the design, fabrication and measurement of 2X2 thermooptic polymer based optical switch. Optical propagation in dielectric waveguides has been analyzed using the semi analytical effective index method and numerical method based on finite difference approach. The iterative solution and successive over relaxation method have been sought for better results of the criterion of sufficient accuracy and improvement of speed of convergence respectively. A description of thermal analysis used for the calculation of the temperature profile and the resulting phase shift in polymer optical waveguide has been investigated. The resulting phase shift due to the induced temperature as a function of the thin film electrodes heater configuration and the applied power have been determined for future device implementation between two adjacent polymer waveguides. The device uses symmetrical and asymmetrical modes interference couplers to perform necessary passive power splitting operations. Electrically controlled gold heater electrodes and chromium heater pads for adhesion were used to perform the switching operation by altering the refractive index of the coupler arms. The new asymmetric structure in terms of index contrast difference between the cladding and waveguiding layers of 2X2 polymer switch was fabricated using ultraviolet curable acrylate adhesive polymers on silicon substrate using photolithography process. A switching time of 7 ms and a crosstalk value of -30 dB were measured. The insertion loss measured was 2 dB. It also has the advantage of being a low cost optical switch with a very low power consumption of 12.26 mW.

ABSTRAK

Tesis ini adalah berkaitan dengan pembangunan suis optik, di mana ia merupakan komponen penting dalam rangkaian pemultipleks pembahagi panjang gelombang. Suis optik 2X2 jenis pandu gelombang berasaskan pengganding berarah interferometer am beroperasi dalam mod tunggal pada panjang gelombang 1550 nm telah direkabentuk dan dibikin menggunakan termooptik polimer. Tiga topik penyelidikan telah disepadukan melalui penggunaan bahan-bahan polimer dalam peranti-peranti fotonik. Topik tersebut adalah, satu perumusan unik bagi model dua dan tiga dimensi pandu gelombang satah menggunakan MATLAB untuk penyelakuan jitu pandu gelombang yang lurus dan bengkok. Keduanya, analisis terma digunakan bagi penghitungan susuk suhu dan keputusan anjakan fasa akibat dari pemanas elektrod filem nipis ke atas bahan polimer menggunakan MATLAB bagi tujuan fungsi pensuisan dan akhirnya, rekabentuk, pembikinan dan pengukuran suis optik 2X2 berasaskan termooptik polimer. Perambatan optik dalam pandu gelombang dielektrik telah dianalisa menggunakan kaedah indek berkesan separuh beranalisis dan kaedah berangka berasaskan pendekatan perbezaan terhingga. Penyelesaian berlelar dan kaedah santaian berturutan telah digunakan untuk mendapatkan keputusan yang lebih baik bagi kriteria kejituan dan kelajuan penumpuan penyelesaian tersebut. Perihalan analisis terma yang digunakan untuk penghitungan susuk suhu dan keputusan anjakan fasa dalam pandu gelombang polimer telah diselidiki. Keputusan anjakan fasa akibat suhu teraruh sebagai fungsi tatarajah elektrod pemanas filem nipis dan kuasa kenaan telah ditentukan bagi tujuan pelaksanaan di masa hadapan antara dua pandu gelombang polimer yang bersebelahan. Peranti ini menggunakan gangguan pengganding mod simetri dan tak simetri untuk melakukan operasi pemisahan kuasa secara pasif. Elektrod pemanas diperbuat dari emas dan pad diperbuat dari kromium bagi tujuan rekatan yang dikawal secara elektrik digunakan untuk melakukan operasi pensuisan dengan mengubah indek biasan lengan pengganding. Satu struktur tak simetri dengan perbezaan indek biasan di antara lapisan penyalutan dan pandu gelombang bagi suis optik 2X2 telah dibikin menggunakan acrylate polimer rekatan terawet ultraungu di atas substrat silicon menggunakan proses fotolitografi. Masa pensuisan 7 ms dan cakap silang -30 dB telah diukur. Kehilangan masukan yang telah diukur adalah 2 Ia juga mempunyai kelebihan sebagai suis optik yang murah dengan dB. penggunaan kuasa yang sangat rendah sebanyak 12.26 mW.

TABLE OF CONTENTS

TITLE

CHAPTER

1

DECLARATION	ii
DEDICATIONS	iii
ACKNOWLEDGEMENTS	iv
PUBLICATIONS, AWARDS AND PATENT	vi
ABSTRACT	ix
ABSTRAK	Х
TABLE OF CONTENTS	xi
LIST OF TABLES	xvii
LIST OF FIGURES	xix
LIST OF SYMBOLS	xxviii
LIST OF ABBREVIATIONS	XXX
LIST OF APPENDICES	xxxii

INTR	ODUCTION	1
1.1	Background	1
1.2	Optical switching	4
1.3	Motivation	5
1.4	Statement of the problem	8
1.5	Objective of the research	8
1.6	Scope of the research	9
1.7	Directional coupler thermooptic	
	polymer switch	9
1.8	Thesis outline	11

PAGE

PHOTONIC SWITCHING DEVICE

TECH	INOLO	DGY	14
2.1	Introduction		
2.2	Typical switching applications		
2.3	Photo	nic switch technology	17
	2.3.1	Micro-electro-mechanical switch	17
	2.3.2	Electrooptic switch	18
	2.3.3	Acoustooptic switch	19
	2.3.4	Liquid crystal switch	20
	2.3.5	Thermooptic switch	20
	2.3.6	Semiconductor optical amplifier	
		switch	21
	2.3.7	Miscellaneous optical switch	
		technology	22
2.4	Comp	arison of different switching	
	techno	ology	23
2.5	Wave	guide based switch and related	
	work	published	24
2.6	Summ	nary	36

THEORETICAL FOUNDATION AND

MODE ANALYSIS				
3.1	Introduction			
3.2	Wave equation in homogeneous media	38		
3.3	Analysis of optical waveguides	44		
	3.3.1 Finite difference method	46		
	3.3.2 Effective index method	48		
3.4	Dielectric waveguides	49		
3.5	Plane wave analysis of dielectric			
	waveguides	50		
3.6	Analysis by effective index method	57		
3.7	Analysis by numerical approach	59		
3.8	Directional coupler	64		

74

74

75

76

78

79

85

3.9	Coupled mode theory	65
3.10	Crosstalk	69
3.11	Bend waveguide structures	70
3.12	Formulation of governing equation	
	for bend channel waveguide	70
3.13	Conclusions	73

4

5

THERMAL ANALYSIS:

4.5

INDUCED TEMPERATURE PROFILES OF THERMOOPTIC POLYMER WAVEGUIDES 4.1 Introduction 4.2 Design consideration for thermal analysis 4.3 Thermal analysis 4.3.1 One-dimensional model 4.3.2 Two-dimensional model

4.4 Induced temperature distribution 81

Induced phase shift 4.6 Calculation of the optimum position of the electrode heater relative to the waveguide branches 86 4.7 Characterization of a heater electrode

material 88 4.8 Results and discussions 89 4.9 Conclusions 91

DESIGN AND SIMULATION 93 5.1 93 Introduction 5.2 94 Materials Polymers 94 5.2.1 5.3 97 Device structures 5.3.1 Design of BSC channel waveguides and cladding layers 98

5.3.2 Design of S-bend waveguides 102

	5.3.3 Design of 2X2 DCTOPS	105
5.4	Simulation of 2X2 DCTOPS	107
5.5	Switching characteristics	112
5.6	Mask design	115
5.7	Conclusions	118

REA	LIZAT	ION OF 2X2 DIRECTIONAL	
COU	PLER 1	FHERMOOPTIC POLYMER	
SWI	TCH (22	X2 DCTOPS)	120
6.1	Introd	uction	120
6.2	Gener	al processing procedures	121
	6.2.1	Surface treatment of silicon	
		substrate	121
	6.2.2	Polymer layer coating	122
	6.2.3	UV curing	122
6.3	Fabric	cation process of the buried square	
	core c	hannel waveguides	122
	6.3.1	Preparation of substrate and	
		materials	123
	6.3.2	Spin coating of under cladding	
		polymer films	123
	6.3.3	Photolithography for waveguides	
		patterning	132
		6.3.3.1 Photoresist application	132
		6.3.3.2 Soft baking	133
		6.3.3.3 Mask alignment and	
		exposure	134
		6.3.3.4 Development	135
		6.3.3.5 Hard baking	135

6.3.4	Inductively coupled plasma	
	etching	136
6.3.5	Masks removing	137
6.3.6	Core layer coating	137

	6.3.8	Spin coating of upper cladding	138		
6.4	Fabric	Fabrication process of heater electrodes			
	and he	eater pads	139		
	6.4.1	Seed metal evaporation	142		
	6.4.2	Formation of heater electrodes	143		
		6.4.2.1 Au plating for heater			
		electrodes	144		
	6.4.3	Formation of heater pads	145		
		6.4.3.1 Au plating for heater pads	145		
	6.4.4	Wet chemical etching for Au			
		seed metal	145		
	6.4.5	ICP etching for Cr seed metal	147		
	6.4.6	Pyrex lid bonding	147		
6.5	Packa	Packaging of the designed devices			
	6.5.1	Wafer device dicing	148		
	6.5.2	Polishing	148		
	6.5.3	Pigtailing	148		
	6.5.4	Wire bonding	149		
6.6	Concl	usions	149		

7

MEASUREMENTS AND

CHARACTERIZA	TIONS OF
---------------------	-----------------

THE	DEVIC	CES	151			
7.1	Introd	Introduction				
7.2	Prism	coupling measurements	152			
7.3	Chara					
	polym	ner layers	157			
	7.3.1	Under cladding thickness	157			
	7.3.2	Waveguides etch depth	158			
	7.3.3	Core coating thickness	158			
	7.3.4	Planarization coating	159			
7.4	Chara	Characterization of waveguides				
	linewi	idth	161			

7.5	Characterization of heater electrodes				
	and heater pads				
7.6	Devic	es characterizations	166		
	7.6.1	Experimental setup for devices			
		characterizations	167		
	7.6.2	Switching characteristics	169		
		7.6.2.1 Near field patterns	169		
		7.6.2.2 Switching curves	171		
		7.6.2.3 Wavelength dependent loss	178		
		7.6.2.4 Minimum input power			
		measurements	179		
		7.6.2.5 Switching time	181		
7.7	Resul	ts and discussions	183		
7.8	Concl	usions	186		
CON	CLUSI	ONS AND RECOMMENDATIONS			

8	CONCLUSIONS AND RECOMMENDATIONS		
	FOR FURTHER WORK		188
	8.1	Conclusions	188
	8.2	Recommendations for further work	191
REFERENCES			193
Appendices A - F			209 - 222

xvi

LIST OF TABLES

TABLE NO.	TITLE	PAGE
1.1	A comparison of polymers with other common	
	inorganic materials for photonic devices	7
2.1	Photonic switching technology comparison	23
2.2	Summary on the performance comparison of	
	optical switches	31
5.1	General specification of the polymer materials	95
5.2	Design parameters of BSC polymer waveguide	101
5.3	Design parameters of 2X2 DCTOPS	112
5.4	Variable parameters on the mask layout	118
6.1	Fabrication process: Buried square core	
	(BSC) channel waveguides	124
6.2	Detailed process: Fabrication of 2X2 directional	
	coupler thermooptic polymer switch	126
6.3	Fabrication process: Electrodes heater	
	and heater pads	140

	٠	٠	٠
XV	1	1	1

6.4	Recipe of Au etching solution	146
7.1	Measured refractive indices and thickness of ZPU1301 and ZPU1302M for TE and TM polarization	155
7.2	Measurement results for BSC waveguide thickness of wafer Sample 040	161
7.3	Characterization results of the six wafers in the realization of the devices	162
7.4	Simulated and fabricated results for the symmetrical and the asymmetrical 2X2 DCTOPS in terms of its coupling length (L_c)	184
7.5	The characteristics of the measured switches	186

LIST OF FIGURES

FIGURE NO	. TITLE	PAGE
1.1	Basic information distribution topologies	3
1.2	Optical network applications of the devices investigated in this work, indicating (a) optical switching functions (b) optical protection switching and (c) optical add-drop	
	multiplexing (OADM)	11
2.1	Integrated optical Mach-Zehnder interferometer	26
2.2	2X2 Mach-Zehnder inteferometer switch	27
2.3	Schematic diagram of active directional coupler	28
3.1	Typical optical waveguides: (a) slab waveguide (b) buried waveguide (c) air-clad rib waveguide (d) buried rib waveguide (e) surface embedded waveguide and (f) strip waveguide	45
3.2	FD mesh for modeling of a rib waveguide	46
3.3	Locating nodes (a) on center of a mesh cell or (b) on mesh points	46

3.4	Various strip waveguide structures: (a) raised strip	
	(b) ridge guide (c) embedded strip and	
	(d) strip-loaded guide	50
3.5	Schematic diagram of three layers slab waveguide structure	51
3.6	E field profiles for symmetric and asymmetric TE modes for a given structure of d=5 μ m, λ =1.55 μ m, n _{core} =1.61 and n _{sub} =1.569. (a) TE ₀ (b) TE ₁ (c) TE ₂ (d) TE ₃ and (e) TE ₄ . Ey has been normalized to 1 and y axis is in m	56
3.7	(a) A rectangular dielectric waveguide to be solved using the effective index method (b) Solve the slab waveguide problem for each y and obtain effective index profile $n_{eff}(y)$ (c) Solve the slab waveguide problem with the effective index profile $n_{eff}(y)$	58
3.8	Schematic diagram of the III-V integrated optical waveguide operating at 1.55 μm	62
3.9	Normalized effective indices as a function of t for the structure shown in Figure 3.8	62
3.10	Schematic diagram of the GaAs waveguide structure operating at 1.15 μm	63
3.11	Mode effective indices as a function of d for the structure shown in Figure 3.10	63
3.12	Normalized effective indices as a function of d for the structure shown in Figure 3.10	64

3.13	Schematic view of a directional coupler	65
3.14	Bend waveguide with mean radius of curvature R_c	72
4.1	Cross section of the thermally induced waveguide.	
	The electrode heater is position d above the waveguiding	
	layer. Material thermal conductivities, k_1 (Si)=1.5,	
	k_2 (Polymers)=0.2 and k_3 (air)=2.6x10 ⁻⁴ W/m °C	
	(Wang, et. al 1996). All dimensions are in μm	76
4.2	Induced temperature profile distribution across the	
	design structure cross-section shown in Figure 4.1,	
	for t=42 $\mu m,$ B=7 μm and P/L=15 mW/mm	82
4.3	Temperature profile in the waveguide for varying	
	distance under the electrode heater of $\Delta y=2 \ \mu m$	
	and L=1 µm	83
4.4	Temperature distribution in the BSC waveguides	
	when the thin film electrode heater is position	
	symmetrically on top of the waveguide $(d = 0)$	84
4.5	Temperature distribution in the waveguides when	
	the thin film electrode heater is position $d=5 \ \mu m$	
	away from one of the waveguide to be heated	84
4.6	Effective index perturbation profile due to	
	temperature change in the waveguides	86
4.7	Effective index as a function of electrode heater	
	position, d	87

4.8	Difference in effective indices between branches	
	for various waveguide gap, g	87
4.9	(a) Cross-section of the heater electrodes	
	(Cr with Au on top) and (b) equivalent electrical circuit.	
	D_{Au} and D_{Cr} are the thickness of the Au and Cr	
	layers respectively, R_{Au} and R_{Cr} are the resistances	
	of the Au and Cr layers respectively	89
5.1	Refractive index tuning of ZPU12-RI and ZPU13-RI	
	series	96
5.2	Schematic view of design 2X2 DCTOPS	98
5.3	Cross section of the BSC polymer waveguide	99
5.4	Optical mode confinement in symmetric BSC	
	waveguide	100
5.5	Optical mode confinement in asymmetric BSC	
	waveguide	101
5.6	Geometry of the S-bend waveguide	102
5.7	Device length, L as a function of bend radius, R _c	
	for an Offset, O=119 μm and 200 μm respectively	103
5.8	Bending los as a function of bending radius	103
5.9	Optical mode confinement in symmetric BSC	
	S-bend waveguide	104
5.10	Optical mode confinement in asymmetric BSC	
	S-bend waveguide	105

5.11	Vertical cross-section of design 2x2 DCTOPS	105
5.12	Schematic view of 2X2 DCTOPS	106
5.13	Effective indices, Neff as a function of waveguide spacing	108
5.14	Coupling length, Lc as a function of waveguide spacing	108
5.15	Coupling length as a function of various waveguide dimension (w = t)	110
5.16	(a) and (b). Coupling lengths as a function of various waveguide spacing, g	111
5.17	Coupling length as a function of various effective index contrast between the waveguides	111
5.18 (a)	Switching characteristics as a function of temperature change in °C. Condition: When the initial state of switch is cross state. (Cross state: The light is coupled from input port P1 to output port P4)	113
5.18 (b)	Switching characteristics as a function of temperature change in °C. Condition: When the initial state of switch is 3-dB state. (3-dB state: The light is coupled from input port P1 to output port P3 and P4 with 3-dB)	114
5.18 (c)	Switching characteristics as a function of temperature change in °C. Condition: When the initial state of switch is bar state. (Bar state: The light is coupled from input port P1 to output port P3)	114

5.19	Switching characteristic for asymmetrical structure	115
5.20	Mask layout of 2X2 DCTOPS	116
5.21	Magnification of mask layout of coupling region	
	of 2X2 DCTOPS. Green: Waveguides,	117
	Yellow: Electrodes heater and Red: Heater pads	116
5.22	The actual mask layout and full wafer description	
	of design 2X2 DCTOPS. Green: Waveguides,	
	Yellow: Electrodes heater and Red: Heater pads	117
6.1	Polymer film thickness as a function of	
	spinning speed	131
6.2	Pattern differences generated from the use of	
	positive and negative resist	133
6.3	Three methods of optical photolithography for	
	transferring patterns to a thin layer of radiation	
	sensitive materials on top of a substrate	134
64	The align mark used in the photolithography	
	process for precision alignment of electrodes heater	
	on top of the BSC waveguides pattern (200XM)	144
71	Measured refractive index of 7PU1301 for	
/.1	TE polarization	153
		155
7.2	Measured refractive index of ZPU1302M for	
	TE polarization	153
7.3	Measured refractive index of ZPU1301 for	
	TM polarization	154

7.4	Measured refractive index of ZPU1302M for	
	TM polarization	154
7.5	Wavelength dispersion curves for blended polymers	156
7.6	Thickness dependence of refractive index	156
7.7	Under cladding layer with a thickness of 26.9 μ m	157
7.8	Etch depth with SiO ₂ and Si-PR mask layer with a thickness of 8.29 μ m	158
7.9	Core coating with a thickness of 36 μ m. Also shown are the 'dips' after spinning the core polymer layer	159
7.10	Planarization coating thickness reduced to 26.4 µm after second thinning. Also shown was the 'dips' thickness	160
7.11	Planarization coating thickness of 26.1 μ m after final 'thinning'	160
7.12	Parallel waveguides linewidth of 7 μ m, with 8 μ m spacing (M200X)	163
7.13	Heater electrodes and heater pads before seed metal is removed (M50X)	164
7.14	Heater electrodes and heater pads after the seeds metal is removed (M100X)	164
7.15	BSC waveguides under the electrodes heater were not well defined	165

7.16	'Plating attack' – Electrodes heater and the PR	
	is not well defined	166
7.17	2X2 DCTOPS configuration	166
7.18	Experimental setup for devices characterization	168
7.19	Switching characteristic: Initial	170
7.20	Switching characteristic: Switching	170
7.21	Near field pattern of 3-dB coupler	171
7.22 (a)	Measured switching curve 2X2 DCTOPS # 010-3-15 for TM mode polarization. Condition: When light is launched into input port – P1	172
7.22 (b)	Measured switching curve 2X2 DCTOPS # 010-3-15 for TE mode polarization. Condition: When light is launched into input port – P1	172
7.23 (a)	Measured switching curve 2X2 DCTOPS # 010-3-15 for TM mode polarization. Condition: When light is launched into input port – P2	174
7.23 (b)	Measured switching curve 2X2 DCTOPS # 010-3-15 for TE mode polarization. Condition: When light is launched into input port – P2	174
7.24 (a)	Measured switching curve 2X2 DCTOPS # 010-1-20 for TM mode polarization. Condition: When light is launched into input port – P1	175

7.24 (b)	Measured switching curve 2X2 DCTOPS # 010-1-20	
	for TE mode polarization. Condition: When light is	
	launched into input port – P1	175
7.25 (a)	Measured switching curve 2X2 DCTOPS # 040-3-16	
	for TE mode polarization. Condition: When light is	
	launched into input port – P1	176
7.25 (b)	Measured switching curve 2X2 DCTOPS # 040-3-16	
	for TE mode polarization. Condition: When light is	
	launched into input port – P1	176
7.26 (a)	Measured switching curve 2X2 DCTOPS # 040-2-4	
	for TM mode polarization. Condition: When light is	
	launched into input port – P1	177
7.26 (b)	Measured switching curve 2X2 DCTOPS # 040-2-4	
	for TE mode polarization. Condition: When light is	
	launched into input port – P1	177
7.27	Measured wavelength dependent loss	179
7.28	Measured crosstalk as a function of input power	180
7.29	Experimental setup to measure the switching time	181
7.30	Switching time curves measured for the 'ON'	
	and 'OFF' ports	183

LIST OF SYMBOLS

SYMBOL

DESCRIPTION

β	-	Propagation constant
${\cal E}_r$	-	Relative permittivity
${\cal E}_0$	-	Free space permittivity
μ_{0}	-	Free space permeability
λ	-	Optical wavelength in free space
с	-	Speed of light in free space
k	-	Thermal conductivity
k_0	-	Free space wave number
k_T	-	Wave vector transverse component
Δeta	-	Propagation constant difference
Δn	-	Refractive index difference
σ	-	Stefan Boltzmann constant $(5.669 \times 10^{-8} \text{ W/m}^2 \text{K}^4)$
Q	-	Radiated power of the black body
Q_{gen}	-	Power generated per unit volume
Т	-	Temperature
Ε	-	Electric field
Н	-	Magnetic field
${\cal E}_e$	-	Radiation coefficient emissivity of the surface
α	-	Thermal diffusivity
h	-	Convection heat transfer coefficient
K	-	Coupling coefficient
L_c	-	Coupling length
$\partial n / \partial T$	-	Thermooptic coefficient

n	-	Refractive index
n _{TE}	-	TE mode refractive index
n _{TM}	-	TM mode refractive index
n _{eff}	-	Effective refractive index
0	-	S-bends offset
R_c	-	Curvature radius
η_i	-	Effective impedance of the <i>i-th</i> mode
$A_s(z)$	-	Amplitude of the symmetric mode
$A_a(z)$	-	Amplitude of the asymmetric mode
t	-	Thickness of the structure
t _{uc}	-	Upper cladding thickness
t_{lc}	-	Lower cladding thickness
W	-	Waveguide width
ω	-	Angular frequency
D	-	Electrode heater thickness
В	-	Electrode heater width
L	-	Electrode heater length
g	-	Waveguide spacing
Р	-	Applied heating power
d	-	Center-to-center distance between electrode
		heater and the core
N _{sym}	-	Effective index of lowest order system mode
		referred as symmetric mode
Nasym	-	Effective index of lowest order system mode
		referred as asymmetric mode

LIST OF ABBREVIATIONS

AOS	-	Acoustooptic switch
ADM	-	Add-drop multiplexer
000	-	All optical cross connect
AC	-	Alternating current
ATM	-	Asynchronous transfer mode
BOE	-	Buffered oxide etchant
BSC	-	Buried square core
ССМ	-	Chip-to-chip module
CTE	-	Coefficient of thermal expansion
DI	-	Deionized
DWDM	-	Dense wavelength division multiplexing
DUT	-	Device under test
DOS	-	Digital optical switch
DC	-	Directional coupler
DCTOPS	-	Directional coupler thermooptic polymer switch
EI	-	Effective index
EIM	-	Effective index method
EO	-	Electrooptic
FD	-	Finite difference
FDM	-	Finite difference method
FHD	-	Flame hydrolysis deposition
FVFD	-	Full vectorial finite difference
ICP	-	Inductively coupled plasma
IR	-	Infrared
IL	-	Insertion loss
IC	-	Integrated circuit
IP	-	Internet protocol
IDFT	-	Inverse discrete Fourier transform

ISFD	-	Iterative scalar finite difference
LD	-	Laser diode
LANs	-	Local area networks
MZ	-	Mach-Zehnder
MZI	-	Mach-Zehnder interferometer
MEMS	-	Micro-electro-mechanical system
MBOA	-	Modified bifurcation optically active
MCM	-	Multichip-to-multichip
OADM	-	Optical add-drop multiplexer
OXC	-	Optical cross connect
OE	-	Optical-to-electrical
OEO	-	Optical-to-electrical-to-optical
PR	-	Photoresist
PLC	-	Planar lightwave circuit
PDL	-	Polarization dependent loss
KLTN	-	Potassium lithium tantalite niobate
PL	-	Propagation loss
RIE	-	Reactive ion etching
SVFD	-	Semi vectorial finite difference
SOA	-	Semiconductor optical amplifier
ТО	-	Thermooptic
TOC	-	Thermooptic coefficient
3D	-	Three-dimensional
TIR	-	Total internal reflection
TE	-	Transverse electric
ТМ	-	Transverse magnetic
TLS	-	Tunable laser source
2D	-	Two-dimensional
UV	-	Ultraviolet
VFE	-	Vector finite element
VCS	-	Vertical coupling switch
VLSI	-	Very large scale integrated
WDL	-	Wavelength dependent loss
WDM	-	Wavelength division multiplex

LIST OF APPENDICES

А	DERIVATION FOR VARIATIONAL	
	EXPRESSION FROM SCALAR WAVE	
	EQUATION FOR TE MODE	
	POLARIZATION	209
В	FORMULATION FOR ITERATIVE SCALAR	
	FINITE DIFFERENCE USING TAYLOR'S	
	THEOREM AND THE CONVERGENCE	
	PROCESS DERIVED FROM THE	
	SUCCESSIVE OVER RELAXATION (SOR)	
	METHOD	211
С	DERIVATION OF COUPLED MODE	
	EQUATIONS	214
D	DERIVATION FOR VARIATIONAL	
	EXPRESSION FOR BEND WAVEGUIDE	
	IN CYCLINDRICAL POLAR COORDINATE	
	SYSTEM	216
E	DERIVATION FOR TEMPERATURE	
_	PROFILES CALCULATION USING	
	INVERSE DISCRETE FOURIER	
	TRANSFORM (IDFT) METHOD	218
F	POLARIZATION	221
1		

CHAPTER 1

INTRODUCTION

1.1 Background

The world we live in today requires communication on many levels, the most basic of which is human to human. Indeed the invention of the telegraph and the telephone were the answers to this need that irrevocably changed our world and resulted in the creation of widespread telecommunication networks. A similar revolution has occurred in electronics computing devices that has resulted in the need for communication from computer to computer. An ever increasing demand for the acquisition, processing and sharing of information concerning the world and its future course, today, these needs are echoed in the demand for higher bandwidth in telecommunications networks and similarly in computing as a demand for higher processing speeds.

Computing devices for example, may experience a revolution in the near future as processing speed place higher demands on conventional electronics. Communication inside a computer on a board-to-board or perhaps chip-to-chip level may benefit from the implementation of optical interconnection because as frequency increase electrical interconnections experiences higher losses and crosstalk. Optical interconnection provides a means to achieve the same function while consuming less power, which alleviates some of the problems of heat dissipation in integrated circuits. In addition the higher integration densities can be achieved in optical interconnects because of the reduced electromagnetic coupling between adjacent channels compared to electrical connections. Similarly, in telecommunication networks, the tremendous achievements in optical data transmission have resulted in a massive global deployment of optical fiber transmission lines, spanning a total distance that is be measured in the hundreds of millions of kilometers. Up until recently, the story of the progress made in point to point optical fiber transmission has sufficed to capture all the interesting developments in modern optical communications.

As optical comunication technology advances, electronic circuits increase in complexity and performance. This increase also requires an increase in the number of interconnection per chip and in the interconnection speed, otherwise the bottlenecks due to electrical connections created, will limit the overall system performance. The interconnections include: chip-to-chip module (CCM) on a common multichip module, multichip-to-multichip (MCM) module and board-to-board communication through a back plane. The increasing cost in terms of power, size, component count weight and reliability of implementing the required interconnects electrically has motivated serious consideration of replacing electrical interconnects with optical interconnects in optical communication network.

In the last decade, however an interesting evolution has been occurring in the world of optical communication. The major technology issues are now shifting from those of optical links to that actively control over signal paths through various information distribution topologies as depicted schematically in Figure 1.1. This interest has been triggered by the explosive growth in high data rate multimedia traffic over the past few years. Increasing user demands for high performance connections and expanding number of user have initiated the development of fiber to the hub systems and local area or metropolitan area network systems.



Figure 1.1: Basic information distribution topologies

The link topology in Figure 1.1(a) represents the simplest use of optical technology in a communication system. The nodes transmit and receive optical signal and perform all other functions electronically. In a hub design, information is distributed to multiple nodes from a single transmitter. Optical technologies are now being deployed to realize such hubs and a good example of this hub type passive optical network emerging for the distribution of cable television services. In this configuration, fiber is used as the transmission medium, however some optical function such as passive signal distribution and wavelength multiplexing are beginning to permeate into the nodes. Similarly in full network structure shown in Figure 1.1(c), optical technologies provides the links between the nodes, but within the nodes they are utilized for signal processing functions such as protection switching, add-drop multiplexer (ADM) and also provides some switching capability.

The hub and network topologies need not be mutually exclusive and can be combined and be referred to optical network. As optical networks develop, an increasing need for such vital functions as signal distribution, switching, protection and reconfiguration is evident, due to the volume and complexity of network traffic and the high cost of lost high throughput links. In the first generation of optical networks, these functions have been implemented electronically, with optical fiber simply replacing the old copper lines as transmission medium. It is rapidly becoming apparent, however, that the information throughput of the network is limited by bottlenecks at the network nodes where the electronic functions are performed.

The second generation of optical networks is currently under active development and aim to achieve optically transparent paths through a network by removing the electrical components and exploiting the unique properties of optics. This interest has been triggered by current evolving telecommunication networks focusing on network flexibility and transmission capacity, which requires enhanced functionality of photonics integrated circuits for optical communications. In addition, for example, modern wavelength division multiplex (WDM) system (Kaminow *et al.*, 1996; Koga *et al.*, 1996), requires signal routing, coupling and switching devices having large optical bandwidth and to be polarization insensitive.

According to these functionality of photonic integrated circuits for optical communications, optical switch, attenuator, optical modulator, multiplexers and wavelength filter are investigated actively (Kaminow *et al.*, 1996). In these devices, optical switch plays a role of basic device in high bit rate optical network by means of integration with ADM or optical cross connector (OXC) (Brackett, 1990; Borella *et al.*, 1997). Moreover it is used to implement redundant path protection to provide economical protection against fiber cuts and failures for asynchronous transfer mode (ATM), internet protocol (IP) and dense wavelength division multiplexing (DWDM) transmission systems. These are the basic premise of optical switching that by replacing existing electronic network switches with optical ones the need for optical to electronic to optical (OEO) conversion is removed. Clearly the advantages of being able to avoid the OEO conversion stages are significant.

1.2 Optical switching

Lightwave transmission via low-loss, low-dispersion single mode fiber has become the choice for high capacity point-to-point communication systems. From the viewpoint of transmission, fiber offers the potential of enormous information bandwidth. To preserve this advantage in future lightwave networks, it is important that the total information capacity of the network not be limited by the switch that provides connectivity. The current optical cross connect (OXC) uses an electrical core for switching, where the optical signals are first converted to electrical signals, which are then switched by electronic switch and finally converted back to optical signals or in other word, optical to electrical to optical switching (OEO) for further transmission. Therefore, electronic switching devices have limitations on both the data rate that they will handle and the switching reconfiguration rates achievable.

The main attraction of optical switching is that it enables routing of optical data signals without the need for conversion to electrical signals or sometimes referred to all optical cross connect (OOO). In contrast to OEO, when the data rate increases, an expensive transceivers and electronic switch core have to be replaced. The OOO is independent of data rate and ready for future data rate upgrades. Since, there is no need for expensive and power hungry high speed electronic switches, transmitters and receivers, the system becomes less expensive. In addition, the reduction of complexity improves reliability of the OOO crossconnect compared to OEO solutions.

The key component for OOO crossconnect is an optical switch. Optical switches are attractive components for routing of high bit rate optical signals in all optical networks, for circuit protection switching to by-pass a faulty system or cable and for the space stage of transparent OXCs. Switching of cable TV in local area networks (LANs), high bit rate data in optical backplanes of a computer and optical signals in sensors may be further applications in the telecommunications area. Optical switches suitable for the above mentioned application could be implemented at low cost by using polymer waveguide technology.

1.3 Motivation

There is an increasing need for optical switch matrices for routing, switching, protection switching, cross connection and add-drop multiplexing. The recent progress in WDM lightwave communication system will further increase the

necessity of optical switch modules. Several optical switch architectures have been proposed and implemented in silica on silicon or glass substrates (Shibata, 2002; Syahriar *et al.*, 1998), Ti-LiNbO₃ (Lu *et al.*, 1994; Krahenbuhl *et al.*, 2002) and semiconductors (Hamamoto *et al.*, 1993; Kang *et al.*, 2000). The planar lightwave circuit (PLC) technology has been used to develop large scale matrix switches with good performance, however these switches are slow due to the intrinsic optical coupling efficiency resulting from a mismatch of the mode field between the PLC and the optical device (Nakagawa *et al.*, 1998). Ti-LiNbO₃, on the other hand is fast but they have large polarization dependence, and are impossible to monolithically integrate with active devices. As for semiconductor based switches, various types have been proposed. Semiconductor optical amplifier gate type switches (Hamamoto *et al.*, 1996) exhibit low insertion loss and quite high extinction ratios. However, they have the disadvantage of switching speed, which is limited by the carrier lifetimes. This will causes the pattern effect, which result in signal degeneration (D'Alessandro *et al.*, 2001).

On the other hand, polymeric optical devices have attracted large attention recently, because of low costs and high-speed possibilities as well as fabrication flexibility (Pun and Wong, 2002). High speed Mach-Zehnder (MZ) modulator (Wang *et al.*, 1999; Spickermann *et al.*, 1996) and polarization control devices (Lee and Shin, 1997a; Oh *et al.*, 1997a) have been demonstrated using polymers. Since the polymer can be dissolved, it can be cast into almost any shape. Polymers have an additional degree of freedom, the poling field defines the direction of the optic axis. Unique devices having twisted optic axes have been demonstrated by Oh and Shin (1996), a possibility of which did not exist before polymers. Furthermore the polymer devices can be fabricated directly on electronic substrates and assembled with integrated circuits (ICs) to create a hybrid optoelectronic package (Ermer *et al.*, 1992; Oh and Shin, 1996). The performance comparison of different technologies given by Lytel (1994) is shown in Table1.1.

Figure of merit	GaAs	Ti:LiNbO ₃	Polymers
Dielectric constant, ε	12	28	3.5
Refractive index, n	3.5	2.2	1.6
Loss (dB/cm (a) $\lambda = 1.3 \mu m$)	2	0.2	0.5
BW-length product (GHz-cm)	>100	10	>150

 Table 1.1: A comparison of polymers with other common inorganic materials for photonic devices (Lytel, 1994)

There are various factors to determine whether the material is suitable for making high speed devices. The most important of these factors are (i) speed match (ii) dielectric constant and (iii) index change per unit electric field. For high speed devices a good speed match between the traveling electric signal and optical signal is very important. The speed of the electric signal is $\frac{c}{\sqrt{\varepsilon_r}}$ and that of optical signal is

 $\frac{c}{n}$ where c is the speed of light in the free space and \mathcal{E}_r and n are the dielectric constant and the refractive index of the material, respectively. The closer the two

constant and the refractive index of the material, respectively. The closer the two speeds are the longer the interaction length and the more effective the modulation. Large bandwidth-length product is required for material to be used for fabricating high speed switches. Low dielectric constant is desirable for high speed devices because it reduces the response time of the device by reducing the capacitance of the electrode. As the polymer has higher thermooptic coefficient (TOC) of typical value in the order of -10^{-4} °C⁻¹, compared with inorganic materials of typical value in the order of 10^{-5} °C⁻¹, it also reduces the driving power required for the modulator or switch (Toyoda *et al.*, 2000) and suitable for larger switching matrices. Thin film of polymer devices can be easily fabricated on virtually any smooth substrates. Monolithic integration of polymer devices with very large scale integrated (VLSI) circuitry can be realized with less technical complexity. The virtually unlimited variations of molecular design make it possible to tailor the optical and other properties of polymers to meet specific requirements. Therefore, it is the goal of this work to continue to expand the knowledge and applicability of integrated optical devices by proposing a new optical switch configuration using all polymer materials.

1.4 Statement of the problem

Polymer integrated optical devices have great potential for applications in high speed optical interconnects due to their microelectronics processing compatibility, their multilevel high density feasibility and ultra high speed operation capability. However, the fabrication of polymer integrated optical devices is still done through trial and error due to inaccurate design schemes and insufficient characterization of materials and processing steps. Furthermore, the device components should meet practical requirements such as low optical losses, polarization insensitivity, low crosstalk, low power consumption, small size, cost effective manufacture and reproducibility, low insertion loss, wavelength dependence and reliability issues. These are the unsolved problems that motivated this research work.

1.5 Objective of the research

The problem being addressed by the present research work, is therefore the main nobjective of the research and is stated as follows:

To provide accurate model and design schemes for polymer based optical switch. The then polymer based optical switch will be fabricated and tested. The performance of the fabricated polymer based optical switch should give low switching power, low crosstalk, polarization independent and low insertion loss operated at the third telecommunication window with a central wavelength of 1550 nm.

It is too vast for any single research work under a given time frame to cover all topics broadly related and yet separable to realize TO polymer based optical switch. As research is a continuing effort, the present research will focus specifically on the following:

- 1. To choose the TO polymer materials for waveguides core, cladding and the substrate to fabricate an optical switch.
- Modeling and simulation of low loss waveguides structure including straight, bend, parallel and the device configuration compatible with singlemode fiber core dimension for monomode operation at the third telecommunication window, with a central wavelength of 1550 nm.
- Determination of the coupling length variations as a function of waveguide dimension, waveguide gap and effective index difference between the two identical and parallel waveguide branches.
- Calculation of the optimum position of the heater electrodes due to the heater electrodes placed alongside the branch relative to the waveguides core to reduce switching power consumption.
- Design of masks. Three different types of masks need to be designed, one for definition of waveguides, one for the heater electrodes and one for the heater pads.
- 6. Fabrication of TO optical switch with low switching power, low crosstalk, polarization independent and low insertion loss.
- 7. Measurement and characterization of the realized device.

1.7 Directional coupler thermooptic polymer switch

The focus of the work is the development of 2X2 directional coupler thermooptic polymer switch (DCTOPS), specifically using of all TO polymer material. The advantage of investigating a 2X2 DCTOPS is that it can perform a number of useful functions in thin film devices. These functions include power

division, modulation, switching, routing and protection switching without the optical-electrical-optical (OEO) conversion. Additionally, the DCTOPS uses less switching power and small in size, which implies low propagation loss and insertion loss, which is suitable for large switching matrices devices for OXC applications. Furthermore, by using ultraviolet (UV) curable acrylate adhesive polymers instead of their inorganic counterparts such as LiNbO₃ to make these devices will have the following advantages:

- 1. Closer index of refraction match to the optical fibers and polymer waveguides.
- 2. Potential for working with wavelengths from visible to IR region.
- 3. Can be fabricated directly on electronic substrates and assembled with integrated circuits (ICs) to create a hybrid optoelectronics package.
- 4. Ease of fabrication using standard optoelectronics technology.
- 5. Feasibility of large scale integration.
- 6. Suitable for mass production.

In this research, the feasibility of 2X2 DCTOPS has been investigated in detail and mathematical models were developed to predict its behavior. This has led to the development of efficient 2X2 DCTOPS with functions expected to find various uses in the emerging generation of optical networks. Three possible applications of these devices are shown in Figure 1.2.





Figure 1.2: Optical network applications of the devices investigated in this work, indicating (a) optical switching functions (b) optical protection switching and (c) optical add-drop multiplexing (OADM)

In Figure 1.2(a), the 2X2 DCTOPS is used to perform optical switching functions for two different wavelengths consecutively. In Figure 1.2(b), the 2X2 DCTOPS is used as a protection switch, when a primary optical link is severed. An OXC is NXN non-blocking optical switch composed of 2X2 DCTOPS as in general a building block, allows a traffic stream to be modified at a network node as depicted in Figure 1.2(c). The NXN switch is set in a state such that desired data streams are added and dropped at a given node.

1.8 Thesis outline

Much of this work is devoted to the study of the integrated optical 2X2 directional coupler thermooptic polymer switch (DCTOPS). As introduction in Chapter 1, the motivation and reasoning of polymer device research for integrated optical devices are discussed. The objective and the scope of the research study with possible applications of the research device are presented.

Chapter 2 extends the discussion and provides a more detailed reviews of optical switches, which have been developed and related published work by other researchers.

In Chapter 3, the theoretical foundations and mode analysis upon which the integrated optical components in this work are based is discussed. The basic relations and definitions concerned with mode propagation of straight and bend waveguides channel were emphasized. The intent is to produce a detailed mathematical description of optical waveguides as the key elements in the implementation of any waveguide based thermooptic (TO) switch. Next, the numerical simulation is presented. This will serve to provide a proper foundation of understanding of the concepts described in the subsequent chapters.

In Chapter 4, a thermal analysis of the design 2X2 DCTOPS due to the deposition of thin film heater electrodes on top of the device structure is discussed. First, the design consideration and characterization of the thin film heater electrodes is described. The temperature profiles of thermooptic (TO) polymer waveguides are analyzed by inverse discrete Fourier transform method (IDFT). The resulting phase shift due to the induced temperature as a function of the thin film heater electrodes configuration and the applied power have been studied and determined for 2X2 DCTOPS devices implementation.

In Chapter 5, the design considerations that have been made in realizing 2X2 DCTOPS using polymer materials are discussed. The design switch is based on the theory of optical waveguides as the key elements of 2X2 DCTOPS and the thermal analysis for heater electrodes and heater pads discussed in Chapter 3 and Chapter 4 respectively. Two devices switch structures have been designed and simulated, those are symmetrical and asymmetrical. All these consideration will lead to final design of the masks, which will be used for the fabrication of the devices.

In Chapter 6, the details of the cleanroom processing steps for realization of the devices are discussed. The realization of the devices can be divided into two parts: First is the fabrication of the devices in the cleanroom and second is the packaging of the devices. Both the fabrication and packaging have been done during a period as a visiting researcher in the fabrication and packaging laboratories respectively, at Zenphotonics Co. Ltd. of Korea.

In Chapter 7, the measurement results for each step taken during fabrication process in realization of the 2X2 DCTOPS are presented. The 2X2 DCTOPS, which have been realized, is then characterized.

Finally in Chapter 8, a concluding remarks and recommendations for future prospects for this work are given.

implemented to provide mode matching conditions to standard singlemode optical fiber, thereby allowing the integrated devices to be easily packaged.

Employing many of these suggested improvements may improve the switch performance characteristics to a level where the 2X2 DCTOPS presented in this thesis become practical for commercialization. The above description of areas for continuation of this work is not exhaustive, but is designed to convey a flavor of the many doors of investigation, which have been opened. Finally, in addition to the principal application of optical networking, it is hoped that the devices described will find a wider and more far reaching applicability, thereby furthering the dream of integrated optic and fueling the evolution of communication.

REFERENCES

- Abramo, M. T., Roy, E. B. and Lecours, S. M. (1992). Reactive ion etching for failure analysis applications. *Proc. of the 30th*. *Int. Symposium on Reliability Physics*. March 31-April 2. San Diego, CA USA: IEEE, 315–319.
- Bienstman, P., Six, E., Roelens, M., Vanwolleghem, M. and Baets, R. (2002). Calculation of bending losses in dielectric waveguides using eigenmode expansion and perfectly matched layers. *IEEE Photonics Technology Letters*. 14(2): 164-166.
- Bierwitrth, K., Schulz, N. and Arndt, F. (1986). Finite difference analysis of rectangular dielectric waveguide structures. *IEEE Trans. On Microwave Theory and Techniques*. 34(11): 1104-1114.
- Booth, B. L. (1989). Low loss channel waveguides in polymer. *Journal of Lightwave Technology*. 7(10): 1445-1453.
- Booton Jr. R. C. (1992). Computational methods for electromagnetics and microwaves. New York: John Wiley and Sons. 19-58.
- Borella, M. S., Jue, J. P., Banerjee, D., Ramamurthy, B. and Mukherjee, B. (1997). Optical components for WDM lightwave networks. *Proceedings of the IEEE*. 85(8): 1274-1307.
- Bosc, D., Devoldere, N., Bonnel, M., Favennec, J. L. and Pavy, D. (1999). Hybrid silica polymer structure for integrated optical waveguides with new potentialities. *Materials Science and Engineering*. B57: 155-160.

- Boyd, J. T. (1994). *Photonics Integrated Circuits. In Photonics Devices and System.* New York: Hunsperger, R. G. Ed. Marcel Dekker.
- Brackett, C. A. (1990). Dense wavelength division multiplexing networks: principles and applications. *IEEE Journal on Selected Areas in Communications*. 8(6): 948-964.
- Cassidy, S. and Yennadhiou, P. (1988). D-fiber optical space switch employing electrostatic fields. *The 14 European Conference on Optical Communication (ECOC'88)*. September 11–15. Brighton, UK: IEEE, 276-280.
- Chao, F. L. and Wang, W. S. (1994). Analysis of temperature profiles of thermooptic waveguides. *Fiber and Integrated Optics*. 13: 397-406.
- Chen, R. T., Wang, M. R., Sonek, C. and Jannson, T. (1991). Optical interconnection using polymer microstructure waveguides. *Optical Engineering*. 30: 662-665.
- Cheng, Y. T., Drew, G., Gillispie, B., Simko, S. J., Militello, M. C., Waldo, R. A. and Wong, C.A. (1996). Vapor deposited thin gold coatings for high temperature electrical contacts. *Proc. of the 18th. International Conference on Electrical Contacts.* September 16-20. Chicago, IL USA: IEEE, 404-413.
- Chiao, J. C. (2001). Liquid crystal modulators for optical signal switching. *Topical Meeting on Photonics in Switching, Optical Society of America.* 11-15.
- Chinni, V. R., Huang, T. C., Wai, P. K. A., Menyuk, C. R. and Simonis, G. J. (1995). Crosstalk in lossy directional coupler switch. *Journal of Lightwave Technology*. 13(7): 487-493.
- Chlamtac, I., Fumagalli, A. and Kazovsky, L. G. (1996). CORD: Contention resolution by delay lines. *IEEE Journal on Selected Areas in Communications*. 14(5): 1014-1029.

- Chlamtac, I., Elek, V., Fumagalli, A. and Szabo, C. (1997). Scalable WDM network architecture based on photonic slot routing and switched delay lines. *IEEE Proceeding (INFOCOM'97)*. 770-777.
- Culverhouse, D. O., Birks, T. A., Farwell, S. G. and Russell, P. S. J. (1996). All fiber
 3×3 acoustooptic switch. *IEEE Proc. Conference on Lasers and Electrooptics (CLEO'96)*. Europe: 312-312.
- Culverhouse, D. O., Laming, R. I., Farwell, S. G., Birks, T. A. and Zervas, M. N. (1997). All fiber 2×2 polarization insensitive switch. *Photonics Technology Letters*. 9(4): 455-457.
- D'Alessandro, D., Giuliani, G. and Donati, S. (2001). Spectral gain and noise evaluation of SOA and SOA-based switch matrix. *IEE Proceedings on Optoelectronics*. 148(3): 125-130.
- Davies, J. B. and Muliwyk, C. A. (1996). Numerical solution of uniform hollow waveguides with boundaries of arbitrary shape. *IEEE Proceedings*. 113: 277-281.
- Diemeer, M. B. J., Brons, J. J. and Trommel, E. S. (1989). Polymeric optical waveguide switch using the thermooptic effect. *Journal of Lightwave Technology*. 7(3): 449-453.
- Dobbelaere, P. D., Falta, K., Fan, L., Gloeckner, S., and Patra, S. (2002). Digital MEMS for optical switching. *IEEE communication Magazine*. 88-95.
- Dorgeuille, F., Mersali, B. and Feuillade, M. (1996). Novel approach for simple fabrication of high performance InP switch matrix based on laser-amplifier gates. *IEEE Photonics Technology Letters*. 8(9): 1778-1780.
- Ermer, S., Valley, J. F., Lytel, R., Lipscomb, G. F., Eck, T. E. V. and Girton, D. G. (1992). DCM-polymide system for triple stack poled polymer electrooptic devices. *Applied Physics Letters*. 61: 2272-2274.

- Fan, R. and Hooker, R. B. (1998). Hybrid optical switch using polymer waveguides and semiconductor optical amplifiers (SOAs). *The 48th*. *IEEE Conf. on Electronic Components and Technology*. May 25-28. 1006-1011.
- Farwell, S. G., Zervas, M. N. and Laming, R. I. (1998). 2X2 fused fiber null couplers with asymmetric waist cross sections for polarization independent (<0.01 dB) switching. *Journal of Lightwave Technology*. 16(9): 1671-1679.
- Forber, R. A. and Marom, E. (1986). Symmetric directional coupler switches. *IEEE Journal of Quantum Electronics*. 22(6): 911-919.
- Gao, Y., Li, G. Z., Liu, X. D., Liu, E. K., Zhang, X. J., Lu, X. K., Hu, J. H., and Wang, X. (1995). SiGe/Si asymmetric 2X2 electrooptic switch of total internal reflection type. *Applied Physics Letters*. 67: 3379-3380.
- Hadley, G. R. and Smith, R. E. (1995). Full-vector waveguide modeling using an iterative finite-difference method with transparent boundary conditions. *Journal of Lightwave Technology*. 13(3): 465-469.
- Hamamoto, K., Sasaki, T., Matsumoto, T. and Komatsu, K. (1996). Insertion loss free 1×4 optical switch fabricated using bandgap-energy-controlled selective MOVPE . *Electronics Letters*. 32(24): 2265-2266.
- Hamamoto, K., Sugou, S., Komatsu, K. and Kitamura, K. (1993). Extremely low loss 4×4 GaAs/AlGaAs optical matrix switch. *Electronics Letters*. 29(17): 1580-1582.
- Hibino, Y., Okazaki, H., Hida, Y. and Ohmori, Y. (1993). Propagation loss characteristics of long silica based optical waveguide on 5 inch silicon wafers. *Electronics Letters*. 29(21): 1847-1848.
- Hida, Y., Onose, H., and Imamura, S. (1993). Polymer Waveguide Thermooptic Switch with Low Electrical Power Consumption at 1.3 µm. *IEEE Photonic Technology Letters*. 5(7): 782-784.

- Hunsperger, R. G. (1995). *Integrated Optics-Theory and Technology*. Berlin Heidelberg-New York: Springer-Verlag.
- Hunter, D. K. and Andonovic, I. (2001). Approaches to optical internet packet switching. *IEEE Communication Magazine*. 98-104.
- Hwang, W. Y., Oh, M. C., Lee, H. M., Park, H. and Kim, J. J. (1997). Polymeric 2X2 electrooptic switch consisting of asymmetric Y junctions and Mach-Zehnder Interferometer. *IEEE Photonics Technology Letters*. 9(6): 761-763.
- Inoue, Y., Katoh, K. and Kawachi, M. (1992). Polarization sensitivity of silica waveguide thermooptic phase shifter for planar lightwave circuits. *IEEE Photonics Technology Letters*. 4(1): 36-38.
- Kaczmarski, P., Van de Capelle, J. P., Lagasse, P.E. and Meynart, R. (1989). Design of an integrated electro-optic switch in organic polymers. *IEE Proceedings*. 136(3): 152-158.
- Kaminow, I. P., Doerr, C. R., Dragone, C., Koch, T., Koren, U., Saleh, A. A. M., Kirby, A. J., Ozveren, C. M., Schofield, B., Thomas, R. E., Barry, R. A., Castagonozzi, D. M., Chan, V. W. S., Hemenway, B. R., Marquis, D., Parikh, S. A., Steven, M. L., Swanson, E. A., Finn, S. G. and Gallagerm, R. G. (1996). A wideband all-optical WDM network. *IEEE Journal on Selected Areas in Communications*. 14(5): 780-799.
- Kang, S. G., Song, M. K., Park, S. S., Lee, S. H., Hwang, N., Lee, H. T., Oh, K. R., Joo, G. H. and Lee, D. (2000). Fabrication of semiconductor optical switch module using laser welding technique. *IEEE Transactions on Advanced Packaging and Manufacturing Technolog. Part B*, 23 (4): 672 –680.
- Kawachi, M. (1990). Silica waveguides on silicon and their application to integrated optics components. *Journal of Optical and Quantum Electronics*. 22: 391-416.

- Keil, N., Weinert, C., Wirges, W., Yao, H. H., Yilmaz, S., Zawadski, C., Schneider, J., Bauer, J., Bauer, M., Losch, K., Satzke, K., Wischmann, W. and Wirth, J. V. (2000). Thermooptic vertical coupler switches using hybrid polymer/silica integration technology. *Electronics Letters*. 36(5): 430-431.
- Keil, N., Yao, H. H. and Zawadski, C. (1996a). Polymer waveguide optical switch with < - 40 dB polarization independent crosstalk. *Electronics Letters*. 32(7): 655-657.
- Keil, N., Yao, H. H. and Zawadski, C. (1996b). 2X2 digital optical switch realized by low cost polymer waveguide technology. *Electronics Letters*. 32(16): 1470-1471.
- Keil, N., Yao, H. H., and Zawadzki, C. (1996c). Optical switches with low crosstalk based on low cost polymer waveguide technology. *Conference on Lasers and Electro-optics (CLEO'96)*. September 8-13. Europe: 20.
- Keil, N., Yao, H. H., Zawadski, C. and Strebel, B. (1994). 4X4 polymer thermooptic directional coupler switch at 1.55 µm. *Electronics Letters*. 30(8): 639-640.
- Keil, N., Yao, H. H., Zawadski, C., Losch, K., Satzke, K., Wischmann, W., Wirth, J. V., Schneider, J., Bauer, J. and Bauer, M. (2001). Hybrid polymer/silica vertical coupler switch with < -32 dB polarization independent crosstalk. *Electronics Letters*. 37(2): 89-90.
- Keil, N., Yao, H. H., Zawadzki, C., and Strebel, B. (1995). Rearrangeable nonblocking polymer waveguide thermooptic 4X4 switching matrix with low power consumption at 1.55 µm. *Electronics Letters*. 31(5): 403-404.
- Kim, C. M. and Kim, D. G. (1998). Influence of parasitic couplings in bending sections on directional coupler optical switching. *Journal of Optical and Quantum Electronics*. 30(2): 133-140.

- Kinder, B. M. and Tansley, T. L. (1998). A comparative study of photoenhanced wet chemical etching and RIE of GaN epilayers grown on various substrates. *Proc. Conf. on Optoelectronic and Microelectronic Materials Devices*. December 14-16. Perth, Australia: 195-198.
- Klunder, D. J. W. (1997) Thermo-optical tuning of Mach-Zehnder interferometers. *Traineeship Report at IBM Zurich Laboratory*. 28-30.
- Knox, R. M. and Toulios, P. P. (1970). Integrated circuits for the millimeter through optical frequency range. *Proc. M. R. I. Symp. of submillimeter waves*. Fox. J. Ed. Brooklyn. New York: Polytechnic Press. 497-516.
- Kobayashi, J., Matsuura, T., Hida, Y., Sasaki, S. and Maruno, T. (1998). Flourinated polymide wabeguides with low polarization dependent loss and their application to thermooptic switches. *Journal of Lightwave Technology*. 16(6): 1024-1029.
- Koga, M., Hamazumi, Y., Watanabe, A., Okamato, S., Obara, H., Sato, K., Okuno, M. and Suzuki, S. (1996). Design and performance of an optical path cross connect system based on wavelength path concept. *Journal of Lightwave Technology*. 14(6): 1106-1119.
- Kokkas, A. G. (1974). "Thermal analysis of multiple layer structures." *IEEE Transaction on Electron Devices*. 21(11): 675-681.
- Korotky, S. K. (1986). Three space representation of phase mismatch switching in coupled two state optical systems. *IEEE Journal of Quantum Electronics*. 22(6): 952-958.
- Koshiba, M. (1990). *Optical waveguide analysis*. New York, USA: McGraw-Hill. 1-14.

- Krahenbuhl, R., Howerton, M. M., Dubinger, J. and Greenblatt, A. S. (2002). Performance and modeling of advanced Ti:LiNbO₃ digital optical switches. *Journal of Lightwave Technology*. 20(1): 92-99.
- Lagasse, P., De Zutter, D., Young, T. P. and Dillon, B. M. (1988). COST-216 comparative study of eigenmode analysis methods for single and coupled integrated optical waveguides. 14th. European Conference on Optical Communications (ECOC'88). September 11-15. Brighton, UK: 296-299.
- Lai, Q., Hunziker, W. and Melchior, H. (1998). Low power compact 2X2 thermooptic silica on silicon waveguide switch with fast response. *IEEE Photonics Technology Letters*. 10(5): 681-683.
- Lee, M. H., Min, Y. H., Ju, J. J., Do, J. Y. and Park. S. K. (2001). Polymer electrooptic 2X2 switch consisting of bifurcation optical active waveguides and a Mach-Zehnder Interferometer. *IEEE Journal on Selected Topics in Quantum Electronics*. 7(5): 812-818.
- Lee, M. H., Min, Y. H., Park, S., Ju, J. J., Do, J. Y. and Park, S. K. (2002). Fully packaged polymeric four arrayed 2X2 digital optical switch. *IEEE Photonics Technology Letters*. 14(5): 615-617.
- Lee, S. S. and Shin, S. Y. (1997a). Polarization-insensitive digital optical switch using electro-optic polymer rib waveguide. *Electronics Letters*. 33(4): 314-316.
- Lee, S. S., Ahn, S. W., and Shin, S. Y. (1997b). Electrooptic polymer digital optical switch with photobleached waveguides and a self-aligned electrode. *Electronics Letters*. 33(4): 314-316.
- Lee, S. S., Lin, L. Y. and Wu, M. C. (1995). Surface micromachined free space fiber optic switches. *Electronics Letters*. 31(17): 1481-1482.
- Lide, D. R. and Frederikse, H. P. R. (1994). *CRC handbook of Chemistry and Physics*. Boca Raton, Florida, USA: CRC Press.

- Lin, L. Y., Shen, J. L., Lee, S. S., Su, G. D. and Wu, M. C. (1997). Microactuated micro-XYZ stages for free-space micro-optical bench. *Proceedings of the 10th*. *Micro Electro Mechanical Systems (MEMS' 97)*. January 26-30. Nagoya, Japan: 43-48.
- Lin, S., Feng, W., Powelson, J. C., Feuerstein, R. J., Bintz, L. J., Tomic, D. and Mickelson, A. R. (1996). Scattering induced crosstalk in active directional couplers. *Journal of Lightwave Technology*. 14(9): 2012-2025.
- Liu, Y. L., Liu, E. K., Li, G. Z., Zhang, S. L., Luo, J. S., Zhou, F., Cheng, M. Q., Li,
 B. C. and Ge, H. (1994). Novel silicon waveguide switch based on total internal reflection. *Applied Physics Letters*. 64: 2079-2081.
- Lu, B., Zhou, P., Lu, Y. C., Cheng, J., Leibenguth, R. E., Adams, A. C., Zilko, J. L., Zolper, J. C., Lear, K. L., Chalmers, S. A. and Vawter, G. A. (1994).
 Reconfigurable binary optical routing switches with fan-out based on the integration of GaAs/AlGaAs surface-emitting lasers and heterojunction phototransistors. *IEEE Photonics Technology Letters*. 6(2): 222-226.
- Lusse, P., Stuwe, P., Schule, J and Unger, H. G. (1994). Analysis of vectorial mode fields in optical waveguides by a new finite difference method. *Journal of Lightwave Technology*. 12(3): 487-493.
- Lytel, R. (1994). EO polymer materials and devices: From research to reality. *IEEE Nonlinear Optic: Material, Fundamental and Applications (NLO' 94)*. July 25-29. 3-5.
- Marcatili, E. A. J. (1969). Dielectric rectangular waveguide and directional coupler for integrated optics. *Bell System Technology Journal*. 48: 2071-2102.
- Marom, E., Ramer, O. G. and Ruschin, S. (1984). Relation between normal mode and coupled-mode analyses of parallel waveguides. *IEEE Journal of Quantum Electronics*. 20(12): 1311-1319.

- Miyagawa, Y., Tanaka, M., Nakadate, H., Nakao, S. and Miyagawa, S. (2000).
 Process simulator for plasma enhanced sputter deposition system. *Conf. on Ion Implantation Technology*. September 17-22. Alpbach, Austria: 213 216.
- Moller, B. A., Jensen, L., Laurent-Lund, C. and Thirstrup, C. (1993). Silica waveguide thermooptic phase shifter with low power consumption and low lateral heat diffusion. *IEEE Photonics Technology Letters*. 5(2): 1415-1418.
- Moosburger, R., Brose, E., Fischbeck, G., Kostrzewa, C., Schuppert, B. and Petermann, K. (1996a). Robust digital optical switch based on a novel patterning technique for oversized polymer rib waveguides. *Proc. of the 22nd*. *European Conference on Optical Communication (ECOC'96).* 2: September 15-19. Oslo: 67-70.
- Moosburger, R., Fischbeck, G., Kostrzewa, C. and Petermann, K. (1996b). Digital optical switch based on oversized polymer rib waveguides. *Electronics Letters*. 32(6): 544-545.
- Nakagawa, G., Yamamoto, T., Sasaki, S., Norimatsu, M., Yamamoto, N., Nosaka, T., Terada, K., Tanaka, K., Miura, K., and Yano, M. (1998). High power and high sensitivity planar lightwave circuit module incorporating a novel passive alignment method. *Journal of Lightwave Technology*. 16(1): 66-72.
- Nishihara, H., Haruna, M. and Suhara, T. (1989). *Optical Integrated Circuits*. New York: Mc Graw-Hill. 325-330.
- Oh, M. C. and Shin, S. S. (1996). Polymeric polarization independent modulator incorporating twisted optic axis waveguide polarization converters. *IEEE Photonics Technology Letters*. 8(11): 1483-1485.
- Oh, M. C., Hwang, W. Y. and Kim, J. J. (1997a). Integrated optic polarization controlling devices using electro-optic polymers. *ETRI Journal*. 18(4): 287-299.

- Oh, M. C., Hwang, W. Y., Lee, H. M., Han, S. G. and Won, Y. H. (1997b). Electrooptic polymer modulators operating in both TE and TM modes incorporating a vertically tapered cladding. *IEEE Photonics Technology Letters*. 9(9): 1232-1234.
- Oh, M. C., Lee, H. J., Lee, M. H., Ahn, J. H. and Han, S. G. (1998). Asymmetric Xjunction thermooptic switches based on flourinated polymer waveguides. *IEEE Photonics Technology Letters*. 10(6): 813-815.
- Park, H. S., Song, K. W., Yun S. H. and Kim, B. Y. (2002). All-fiber wavelengthtunable acoustooptic switches based on intermodal coupling in fibers. *Journal* of Lightwave Technology. 20(10): 1864-1868.
- Patrick, S. S. and Webb, K. J. (1992). A variational vector finite difference analysis for dielectric waveguides. *IEEE Trans. On Microwave Theory and Techniques*. 40(4): 692-698.
- Pesach, B., Bartal, G., Refaeli, E., Agranat, A. J., Krupnik, J. and Sadot, D. (2000). Free space optical cross-connect switch by the use of electrography. *Applied Optics*. 39(5): 746-758.
- Pun, E.Y.B. and Wong, W. H. (2002). Optical polymeric waveguides and devices. Proceedings of IEEE/LEOS Workshop on Fibre and Optical Passive Components. June 5-6. 126-132.
- Renaud, M., Bachmann, M and Erman, M. (1996). Semiconductor optical space switches. *IEEE Journal on Selected Topics in Quantum Electronics*. 2(2): 277-288.
- Ressom, H., Musavi, M. T. and Khan, S. (2001). Intelligent control of critical dimension in photolithography process. *Proc. of the Int. Joint Conf. on Neural Networks*. July 15-19. Washington, DC USA: 486-490.

- Ribeiro R. M., Kawase, L. R., Margulis, W. and Lidgard, A. (1996). Switching in allfibre interferometer using a semiconductor coated D-fibre. *Electronic Letters*. 32(15): 1402-1403.
- Ridder, R. M. (2002). Theory optical basic functions and Microsystems: Application notes. LDG, University of Twente. Enschede, The Netherlands.
- Ridder, R. M. D., Driessen, A., Rikkers, E., Lambeck, P. V. and Diemmer, M. B. J. (1999). Design and fabrication of electrooptic polymer modulators and switches. *Optical materials*. 12: 205-214.
- Rivera, M. (1995). A finite difference BPM analysis of bent dielectric waveguides. Journal of Lightwave Technology. 13(2): 233-238.
- Robertson, M. J., Ritchie, S. and Dayan, P. (1985). Semiconductor waveguides: Analysis of optical propagation in single rib structures and directional couplers. *IEE Proceedings*. Pt. J, 132(6): 336-342.
- Sadiku, M. N. O. (2001). *Numerical techniques in electromagnetics*. Second Edition. London, Washington DC: CRC Press.
- Schweig, E. and Bridges, W. B. (1984). Computer analysis of dielectric waveguides: A finite difference method. *IEEE Trans. on Microwave Theory and Techniques*. 32(5): 531-541.
- Shibata, T. (2002). High performance optical switches integrated with silica-based planar lightwave circuits on Si. *Lasers and Electro-Optics Society (LEOS'02)*.
 2: November 10-14. 730 –731.
- Smith, D. A., D'Alessandro, A., Baran, J. E., Fritz, D. J., Jackel, J. L. and Chakravarthy, R. S. (1996). Multiwavelength performance of an apodized acoustooptic switch. *Journal of Lightwave Technology*, 14(9): 2044-2051.

- Spickermann, R., Peters, M. G. and Dagli, N. (1996). A polarization independent GaAs-AlGaAs electrooptic modulator. *Journal of Quantum Electronics*. 32(5): 764-769.
- Stern, M. S. (1988a). Semivectorial polarized finite difference method for optical waveguides with arbitrary index profiles. *IEE Proceedings. Pt. J*, 135(1): 56-63.
- Stern, M. S. (1988b). Semivectorial polarized H fields solutions for dielectric waveguides with arbitrary index profiles. *IEE Proceedings. Pt. J*, 135(5): 333-338.
- Strand, O. T., Lowry, M. E., Lu, S. Y., Nelson, D. C., Nikkel, D. J., Pocha, M. D. and Young, K. D. (1994). Automated fiber pigtailing technology. *Proc. of the* 44th. Conf. on Electronic Components and Technology. May 1-4. Washington, DC USA: 1000 – 1003.
- Sugita, A., Jinguji, K., Takato, N., Katoh, K. and Kawachi, M. (1990). Bridge suspended silica waveguide thermooptic phase shifter and its application to Mach Zehnder type optical switch. *Transactions IEICE*. E73(1): 239-241.
- Suijten, F. M. M., Diemeer, M. B. J. and Hendriksen, B. (1994). A digital thermooptic 2X2 switch based on non linear optic polymer. *PTT Research Review*. 4(4): 23.
- Sujecki, S., Benson, T. M., Sewell, P. and Kendall, P.C.(1998). Novel vectorial analysis of optical waveguides. *Journal of Lightwave Technology*.16(7): 1329-1335.
- Supa'at, A. S. M., Mohammad, A. B. and Kassim, N. M. (2002a). Modelling techniques for rectangular dielectric waveguides-ribs waveguides. *Jurnal Teknologi*. 36(D): 129-143.

- Supa'at, A. S. M., Mohammad, A. B. and Kassim, N. M. (2002b). Design of buried type polymer based waveguide optical directional coupler. *IEEE Proc. Int. Conf. on Semiconductor Electronics (ICSE'02)*. December 19-21. Penang, Malaysia: IEEE, 397-401.
- Syahriar, A., Syms, R. R. A. and Tate, T. J (1998). Thermooptic interferometric switches fabricated by electron beam irradiation of silica-on-silicon. *Journal of Lightwave Technology*. 16(5): 841-846.
- Syms, R and Cozens, J. (1992). *Optical Guided Waves and Devices*. Berkshire, England: McGraw Hill Book Company.
- Takato N., Jinguji, K., Yasu, M., Toba, H. and Kawachi, M. (1988). Silica based single mode waveguide on silicon and their application to guided wave optical inteferometers. *Journal of Lightwave Technology*. 6(6): 1003-1010.
- Takato, N., Yasu, M. and Kawachi, M. (1986). Low loss high silica single mode channel waveguide. *Electron Letters*. 22: 321-322.
- Thackara, J. I., Chon, J. C., Bjorklund, G. C., Volksen, W and Burland, M. D. (1995). Polymeric electrooptic Mach-Zehnder switches. *Applied Physic Letters*. 67(26): 3874-3876.
- Toyoda, S., Ooba, N., Katoh, Y., Kurihara, T. and Maruno, T. (2000). Low crosstalk and low loss 2X2 thermooptic digital optical switch using silicone resin waveguides. *Electronics Letters*. 36(21): 1803-1804.
- Ushikubo, T., Asabayashi, I., Hashimoto, A. and Ishida, T. (1990). Cladding layer thickness-controlled directional coupler optical switch. *Journal of Lightwave Technology*. 8(2): 259-263.
- Veldhuis, G. J. (1998). Bent waveguide devices and mechano-optical switches.University of Twente. Enschede, The Netherlands: Phd Thesis.

- Vinchant, J. F., Renaud, M., Erman, M., Peyre, J. L., Jarry, P. and Rossiaux, P. P. (1993). InP digital optical switch: Key element for guided wave photonic switching. *IEE Proceedings. Pt. J*, 140(5): 301-307.
- Vukovic, A. (2000). Fourier transformation analysis of optical components and circuits. University of Nottingham. United Kingdom: Phd Thesis.
- Wang, W. K., Lee, H. J. and Anthony, P. J. (1996). Planar silica-glass optical waveguides with thermally induced lateral mode confinement. *Journal of Lightwave Technology*. 14(3): 429-436.
- Wang, W., Shi, Y., Olson, D. J., Lin, W. and Bechtel, J. H. (1999). Push-pull poled polymer Mach-Zehnder modulators with a single microstripline electrode. *IEEE Photonics Technology Letters*. 11(1): 51–53.
- Weierholt, A. J., Mickelson, A. R. and Neegard, S. (1987). Eigenmode analysis of symmetric parallel waveguide couplers. *IEEE Journal of Quantum Electronics*. 23(10): 1689-1700.
- Weierholt, A. J., Neegard, S. and Mickelson, A. R. (1988). Eigenmode analysis of optical switches in LiNbO₃ - Theory and experiments. *IEEE Journal of Quantum Electronics*. 24(12): 2477-2490.
- Xu, L., Perros, H. and Rouskas, G. (2001). Techniques for optical packet switching and optical burst switching. *IEEE Communication Magazine*. 136-142.
- Yang, D. K. (2003). A simulation study of a liquid crystal optical switch based on total internal reflection. *Journal of Optics A: Pure and Applied Optics*. 5: 402-408.
- Yao, S., Mukherjee, B. and Dixit, S. (2000). Advance in photonics packet switching: An overview. *IEEE Communication Magazine*. 84-94.

- Yi, S. H., Park, H. C., Kim, B. W., Park, J. W. and Sung, Y. K. (1996). A comparison between the experimental results and the thermal simulation for the fabrication of micro hot plate. *IEEE Proc. of Int. Conf. on Semiconductor Electronics (ICSE '96)*. November 26-28. Penang, Malaysia: IEEE, 221-224.
- Yokomine, K., Shimizu, N., Miyamoto, Y., Iwata, Y., Love, D. and Newman, K. (2001). Development of electroless Ni/Au plated build-up flip chip package with highly reliable solder joints. *Proc. of the 51st. Conf. on Electronic Components and Technology*. May 29-June 1. Orlando, FL USA: 1384 – 1392.
- Yoshimoto, N., Shibata, Y., Oku, S., Kondo, S. and Noguchi, Y. (1999). Design and demonstration of polarization-insensitive Mach-Zehnder switch using a latticematched InGaAlAs/InAlAs MQW and deep-etched high-mesa waveguide structure. *Journal of Lightwave Technology*. 17(9): 1662-1668.
- Yu, T. K., Yu, C. C. and Orlowski, M. (1993). A statistical polishing pad model for chemical-mechanical polishing. *Technical Digest International Electron Devices Meeting*. December 5-8. Washington, DC USA: 865 – 868.